

TPS65090EVM User's Guide

This guide details the use of the TPS65090 evaluation module, *TPS65090EVM* (referred to as EVM for the remainder of this document).

The TPS65090, front-end power management unit (PMU), is an integrated high-input voltage (6 V–17 V) charger and power path management device including 3 step-down converters, 2 low-dropout regulators (LDO), 7 load-switches, 16-channel 10-bit A/D converter and I²C™ interface.

The EVM facilitates evaluation of the integrated circuit (IC) and serves as a reference design. For more information on the TPS65090, refer to the datasheet: *TPS65090 High Input Voltage Frontend PMU for Mobile Computer*, ([SLVSAU3](#)).

Contents

1	Requirements	2
2	Setup and Operation	2
	2.1 Power Connections	2
3	Headers and Jumpers	3
4	Graphical User Interface (GUI)	4
5	Schematic Diagram	4
6	Board Layout	9
7	Bill of Materials	16
8	References	18

List of Figures

1	TPS65090EVM GUI	4
2	TPS65090EVM Schematic Charger or Power Path and Configuration.....	5
3	TPS65090EVM Schematic Converters and Load Switches.....	6
4	TPS65090EVM Schematic USB to I ² C Interface	7
5	TPS65090EVM Schematic Test Pads	8
6	TPS65090EVM Board Layout, Top Assembly	9
7	TPS65090EVM Board Layout, Bottom Assembly (mirrored)	10
8	TPS65090EVM Board Layout, Top	11
9	TPS65090EVM Board Layout, Internal 2.....	12
10	TPS65090EVM Board Layout, Internal 3.....	13
11	TPS65090EVM Board Layout, Bottom (mirrored).....	14
12	TPS65090EVM Board Layout, Top Silkscreen	15

List of Tables

1	EVM Header and Jumper Descriptions	3
2	TPS65090 Solution, Required Components	16
3	TPS65090EVM Evaluation Components	17

WARNING

EXPORT NOTICE:

Recipient agrees to not knowingly export or re-export, directly or indirectly, any product or technical data (as defined by the U.S., EU, and other Export Administration Regulations) including software, or any controlled product restricted by other applicable national regulations, received from Disclosing party under this Agreement, or any direct product of such technology, to any destination to which such export or re-export is restricted or prohibited by U.S. or other applicable laws, without obtaining prior authorization from U.S. Department of Commerce and other competent Government authorities to the extent required by those laws. This provision shall survive termination or expiration of this Agreement. According to our best knowledge of the state and end-use of this product or technology, and in compliance with the export control regulations of dual-use goods in force in the origin and exporting countries, this technology is classified as follows:

US ECCN: 3E991

EU ECCN: EAR99

And may require export or re-export license for shipping it in compliance with the applicable regulations of certain countries.

1 Requirements

In order to use the EVM, a lab power supply capable of supplying at least the TPS65090 output power at a voltage between 6 V and 17 V and/or a rechargeable multi-cell lithium battery is required. Additionally, a computer running Windows® 7 or Windows XP loaded with the *TPS65090EVM-SW* graphical user interface (GUI) and a mini-USB cable are recommended.

2 Setup and Operation

2.1 Power Connections

Connect the lab power supply to the input labeled AC (AC adapter), J1; pin 1 positive lead and pin 6 negative lead.

Connect the rechargeable Li-Ion battery to J3; pin 1 positive lead and pin 6 negative lead.

By default, the charger and converters are enabled and disabled by external pins. The LDOs are always on, since they additionally provide power to internal blocks.

3 Headers and Jumpers

Many of the 6-pin headers provide Kelvin sense lines, S+ and S– (pins 3 and 4), for sensing the voltage directly at the input or output capacitors.

Table 1. EVM Header and Jumper Descriptions

Reference Designator	Name	Description
J1	V_AC	Input connection for AC adapter
J2	VSYS	Header for power path output system voltage
J3	V_BAT	Header for Li-Ion battery connection
J4	DCDC1	Header for output voltage of switching converter, DCDC1
J5	DCDC2	Header for output voltage of switching converter, DCDC2
J6	DCDC3	Header for output voltage of switching converter, DCDC3
J7	Digital	Header for open drain outputs, each pulled up to J14
J8	VIO	Jumper to select pull-up for I ² C bus, default: USB_3P3
J9	USB_3P3	Header for output of U4, 5-V to 3.3-V LDO
J10	I ² C	Header for I ² C bus
J11	J11	Mini-USB connection to PC for GUI
J12	SCL pull-Up	Jumper to pull-up SCL to J8, default: installed
J13	SDA pull-Up	Jumper to pull-up SDA to J8, default: installed
J14	Output pull-up	Jumper to select pull-up for open-drain outputs
J15	ENC	Jumper to externally enable or disable charger
J16	TS1	Header connection to pin TS1 network
J17	TS2	Header connection to pin TS2 network
J18	EN_DCDC1	Jumper to externally enable or disable DCDC1
J19	EN_DCDC2	Jumper to externally enable or disable DCDC2
J20	EN_DCDC3	Jumper to externally enable or disable DCDC3
J21	LDO1	Header to output voltage of LDO1
J22	LDO2	Header to output voltage of LDO2
J23	FET Out	Header to FET outputs
J24	FET In	Header to FET inputs
J25	Factory Use	Jumper used for firmware install only
JP1	I_VSYS	Solder bridge to optionally measure VSYS current
JP2	I_VBAT	Solder bridge to optionally measure V_BAT inductor current
JP3	I1	Solder bridge to optionally measure DCDC1 inductor current
JP4	I2	Solder bridge to optionally measure DCDC2 inductor current
JP5	I3	Solder bridge to optionally measure DCDC3 inductor current

4 Graphical User Interface (GUI)

The GUI design allows the TPS65090 to easily interface with a PC. The GUI gives the capability to read and write the contents of the I²C registers and simplifies use with radio check boxes, drop-down menus and pushbuttons.




Figure 1. TPS65090EVM GUI

5 Schematic Diagram

The schematic diagram illustrates the circuit connections of the EVM.

This EVM contains many components that are not necessary for an end-product. These additional components are added to simplify evaluation of the IC. In [Section 7](#), the Bill of Materials (BOM), there are two tables; the first table includes the required materials for functionality of the TPS65090 and the second table contains the additional materials added for evaluation.






Figure 3. TPS65090EVM Schematic Converters and Load Switches




Figure 4. TPS65090EVM Schematic USB to I²C Interface




Figure 5. TPS65090EVM Schematic Test Pads

6 Board Layout

This section provides the EVM board layout and illustrations.

Board layout is critical for all high-frequency, switch-mode power supplies. The following figures show the board layout for the EVM printed-circuit board. The nodes with high-switching frequencies and currents are kept as short as possible to minimize trace inductance.

Careful attention has been given to the routing of high-frequency current loops and a single-point grounding scheme is used. See the data sheet for specific layout guidelines.




Figure 6. TPS65090EVM Board Layout, Top Assembly




Figure 7. TPS65090EVM Board Layout, Bottom Assembly (mirrored)




Figure 8. TPS65090EVM Board Layout, Top




Figure 9. TPS65090EVM Board Layout, Internal 2




Figure 10. TPS65090EVM Board Layout, Internal 3




Figure 11. TPS65090EVM Board Layout, Bottom (mirrored)




Figure 12. TPS65090EVM Board Layout, Top Silkscreen

7 Bill of Materials

This EVM contains many components that are not necessary for an end-product. These additional components are added to simplify evaluation of the IC. The first table includes required materials for functionality of the TPS65090 and the second table contains the additional materials added for evaluation.

Table 2. TPS65090 Solution, Required Components

Count	RefDes	Value	Description	Size	Part Number	MFR
8	C1, C5, C8, C14, C20, C38, C39, C47	1 μ F	Capacitor, ceramic,X5R, 25 V, 20%	0402	GRM155R61E105MA12	Murata
11	C11, C17, C23, C35, C36, C48, C49, C50, C51, C52, C53	2.2 μ F	Capacitor, ceramic, X5R, 6.3 V, 10%	0402	GRM155R61A225KE95	Murata
29	C2, C3, C6, C7, C9, C12, C13, C15, C18, C19, C21, C24, C25, C26, C27, C28, C29, C30, C31, C32, C33, C34, C40, C41, C42, C43, C44, C45, C46	10 μ F	Capacitor, ceramic, X5R, 25 V,10%	0603	GRM188R61E106MA73	Murata
13	C37, C55, C56, C57, C58, C59, C60, C61, C62, C63, C65, C66, C67	100 nF	Capacitor, ceramic, 25 V, X5R, 20%	0402	STD	STD
4	C4, C10, C16, C22	4700 pF	Capacitor, ceramic, 50 V, X5R, 10%	0402	STD	STD
2	C54, C64	1 μ F	Capacitor, ceramic, 25 V, X5R, 10%	0603	GRM188R61E105KA12D	Murata
1	D1	1N4148W-7-F	Diode, signal, 300 mA, 75 V, 350 mW	SOD-123	1N4148W-7-F	Diodes
4	L1, L2, L3, L4	2.2 μ H	Inductor, power, 9.2 A, \pm 20%	5 x 5 mm	XAL5030-222ME	Coilcraft
2	Q1, Q2	CSD17304Q3	MOSFET, NChannel, 30 V, 56 A, 9.8 m Ω	QFN3.3x3.3 mm	CSD17304Q3	TI
1	Q3	CSD25401Q3	MOSFET, PChannel, -20 V, 60 A, 8.7 m Ω	QFN3.3X3.3mm	CSD25401Q3	TI
1	Q4	BSS138W-7-F	MOSFET, NChannel, 50 V, 200 mA	SOT323	BSS138W-7-F	Diodes
2	R1, R2	0.01 Ω	Resistor, chip, 1/4 watt, 1%	1206	WSL1206R0100FEA	Vishay
1	R13	0.002 Ω	Resistor, chip, 3/4 watt, 1%	1206	PMR18EZPFV2L00	Rohm
1	R14	3 m Ω	Resistor, chip, 1/16W, 1%	0402	STD	STD
1	R15	1M	Resistor, chip, 1/16W, 1%	0402	STD	STD
2	R18, R19	1 k Ω	Resistor, chip, 1/16W, 1%	0402	STD	STD
2	R20, R21	10 k Ω	Thermistor, NTC, 10 k Ω , 1%	0603	NTCS0603E3103FLT	Vishay
2	R3, R40	330 k Ω	Resistor, chip, 1/16W, 1%	0402	STD	STD
1	R4	110 k Ω	Resistor, chip, 1/16W, 1%	0402	STD	STD
2	R41, R49	470 k Ω	Resistor, chip, 1/16W, 1%	0402	STD	STD
2	R45, R46	3.9 Ω	Resistor, chip, 1/4 watt, \pm 1%	1206	STD	STD
2	R47, R48	4.7 k Ω	Resistor, chip, 1/16W, 1%	0402	STD	STD
2	R5, R6	2.2 k Ω	Resistor, chip, 1/16W, 1%	0402	STD	STD
1	R50	10 Ω	Resistor, chip, 1/4 watt, \pm 1%	1206	STD	STD
2	R7, R8	6.8 k Ω	Resistor, chip, 1/16W, 1%	0402	STD	STD
6	R9, R10, R11, R12, R16, R17	10 k Ω	Resistor, chip, 1/16W, 1%	0402	STD	STD
1	U1	TPS65090RVN	IC, Multi output power management with ADC and battery charger	QFN	TPS65090RVN	TI

Table 3. TPS65090EVM Evaluation Components

Count	RefDes	Value	Description	Size	Part Number	MFR
2	C68, C69	30 pF	Capacitor, ceramic, 50 V, C0G, 10%	0603	STD	STD
3	C70, C71, C72	0.1 μ F	Capacitor, ceramic, 16 V, X7R, 10%	0603	STD	STD
1	C73	1 μ F	Capacitor, ceramic chip, 10 V, \pm 10%	0805	STD	STD
1	C74	0.01 μ F	Capacitor, ceramic, 16 V, X7R, 10%	0603	STD	STD
2	C75, C76	220 pF	Capacitor, ceramic, 50 V, C0G, 5%	0603	STD	STD
1	C77	22 μ F	Capacitor, alum. 10 VDC, \pm 20%	6032	EEE-1AA220WR	Panasonic
1	C78	470 nF	Capacitor, ceramic, 16 V, X7R, 10%	0603	STD	STD
1	C79	2.2 nF	Capacitor, ceramic, 25 V, X7R, 20%	0603	STD	STD
1	C80	2.2 μ F	Capacitor, ceramic, 10 V, X7R, 10%	0603	STD	STD
1	D2	1SMB5922BT3G	Diode, Zener, 7.5 V, 50 mA, 3 W	SMB	1SMB5922BT3G	On Semi
9	J1–J6, J21, J22, J7	PEC06SAAN	Header, male 6 pin, 100-mil spacing,	0.100 in \times 6	PEC06SAAN	Sullins
1	J10	PEC04SAAN	Header, male 4 pin, 100-mil spacing,	0.100 in \times 4	PEC04SAAN	Sullins
1	J11	1734035-2	Connector, recpt, USB-B, mini, 5 pins, SMT	0.354 \times 0.400 in	1734035-2	
2	J23, J24	PEC08DAAN	Header, male 2x8 pin, 100-mil spacing	0.100 in \times 2 \times 8	PEC08DAAN	Sullins
6	J8, J14, J15, J18–J20	PEC03SAAN	Header, male 3-pin, 100-mil spacing,	0.100 in \times 3	PEC03SAAN	Sullins
6	J9, J12, J13, J16, J17, J25	PEC02SAAN	Header, male 2 pin, 100-mil spacing	0.100 in \times 2	PEC02SAAN	Sullins
1	L5	MI1206K900R-10	Bead, ferrite, SMT, 90 Ω , 1.5A	1206	MI1206K900R-10	Laird
4	R22, R23, R24, R38	1M	Resistor, chip, 1/16W, 1%	0402	STD	STD
2	R20, R21	10 k Ω	Thermistor, NTC, 10 k Ω , 1%	0603	NTCS0603E3103FLT	Vishay
9	R25, R28, R30, R32, R34, R36, R37, R44, R57	0 Ω	Resistor, chip, 1/16W, 1%	0603	STD	STD
0	R26, R27, R29, R31, R33, R35	0 Ω	Resistor, chip, 1/16W, 1%	0603	STD	STD
0	R39	0 Ω	Resistor, chip, 1/16W, 0.1%	0603	STD	STD
0	R42, R43	50 k Ω	Potentiometer, single slide, 50 k Ω , 0.1 W, 20%	0.378 \times 0.217 in		Copal
2	R51, R52	33 Ω	Resistor, chip, 1/16W, 1%	0603	Std	Std
2	R53, R59	33 k Ω	Resistor, chip, 1/16W, 1%	0603	Std	Std
1	R54	1.5 k Ω	Resistor, chip, 1/16W, 1%	0603	Std	Std
1	R55	1.2 M Ω	Resistor, chip, 1/16W, 1%	0603	Std	Std
1	U2	MSP430F5529IPN	IC, mixed signal microcontroller	TQFP-80	MSP430F5529IPN	TI
1	U3	TPD4E004DRY	IC, 4-chan ESD-protection array	SON-6	TPD4E004DRY	TI
1	U4	TPS73533DRB	IC, 500 mA, low quiescent current, ultra-low noise, high PSRR LDO, 3.3 V	SON-8	TPS73533DRB	TI
1	Y1	24.0 MHz	Crystal, SMT quartz crystal	0.484 \times 0.190 in	ECS-240-20-5PX-TR	CTS
1	--		PCB, 4.2 in \times 4.2 in \times 0.062 in		PWR108	Any

8 References

1. *TPS65090 High Input Voltage Frontend PMU for Mobile Computer*, ([SLVSAU3](#))

EVALUATION BOARD/KIT/MODULE (EVM) ADDITIONAL TERMS

Texas Instruments (TI) provides the enclosed Evaluation Board/Kit/Module (EVM) under the following conditions:

The user assumes all responsibility and liability for proper and safe handling of the goods. Further, the user indemnifies TI from all claims arising from the handling or use of the goods.

Should this evaluation board/kit not meet the specifications indicated in the User's Guide, the board/kit may be returned within 30 days from the date of delivery for a full refund. THE FOREGOING LIMITED WARRANTY IS THE EXCLUSIVE WARRANTY MADE BY SELLER TO BUYER AND IS IN LIEU OF ALL OTHER WARRANTIES, EXPRESSED, IMPLIED, OR STATUTORY, INCLUDING ANY WARRANTY OF MERCHANTABILITY OR FITNESS FOR ANY PARTICULAR PURPOSE. EXCEPT TO THE EXTENT OF THE INDEMNITY SET FORTH ABOVE, NEITHER PARTY SHALL BE LIABLE TO THE OTHER FOR ANY INDIRECT, SPECIAL, INCIDENTAL, OR CONSEQUENTIAL DAMAGES.

Please read the User's Guide and, specifically, the Warnings and Restrictions notice in the User's Guide prior to handling the product. This notice contains important safety information about temperatures and voltages. For additional information on TI's environmental and/or safety programs, please visit www.ti.com/esh or contact TI.

No license is granted under any patent right or other intellectual property right of TI covering or relating to any machine, process, or combination in which such TI products or services might be or are used. TI currently deals with a variety of customers for products, and therefore our arrangement with the user is not exclusive. TI assumes no liability for applications assistance, customer product design, software performance, or infringement of patents or services described herein.

REGULATORY COMPLIANCE INFORMATION

As noted in the EVM User's Guide and/or EVM itself, this EVM and/or accompanying hardware may or may not be subject to the Federal Communications Commission (FCC) and Industry Canada (IC) rules.

For EVMs **not** subject to the above rules, this evaluation board/kit/module is intended for use for ENGINEERING DEVELOPMENT, DEMONSTRATION OR EVALUATION PURPOSES ONLY and is not considered by TI to be a finished end product fit for general consumer use. It generates, uses, and can radiate radio frequency energy and has not been tested for compliance with the limits of computing devices pursuant to part 15 of FCC or ICES-003 rules, which are designed to provide reasonable protection against radio frequency interference. Operation of the equipment may cause interference with radio communications, in which case the user at his own expense will be required to take whatever measures may be required to correct this interference.

General Statement for EVMs including a radio

User Power/Frequency Use Obligations: This radio is intended for development/professional use only in legally allocated frequency and power limits. Any use of radio frequencies and/or power availability of this EVM and its development application(s) must comply with local laws governing radio spectrum allocation and power limits for this evaluation module. It is the user's sole responsibility to only operate this radio in legally acceptable frequency space and within legally mandated power limitations. Any exceptions to this are strictly prohibited and unauthorized by Texas Instruments unless user has obtained appropriate experimental/development licenses from local regulatory authorities, which is responsibility of user including its acceptable authorization.

For EVMs annotated as FCC – FEDERAL COMMUNICATIONS COMMISSION Part 15 Compliant

Caution

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

FCC Interference Statement for Class A EVM devices

This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his own expense.

FCC Interference Statement for Class B EVM devices

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

For EVMs annotated as IC – INDUSTRY CANADA Compliant

This Class A or B digital apparatus complies with Canadian ICES-003.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

Concerning EVMs including radio transmitters

This device complies with Industry Canada licence-exempt RSS standard(s). Operation is subject to the following two conditions: (1) this device may not cause interference, and (2) this device must accept any interference, including interference that may cause undesired operation of the device.

Concerning EVMs including detachable antennas

Under Industry Canada regulations, this radio transmitter may only operate using an antenna of a type and maximum (or lesser) gain approved for the transmitter by Industry Canada. To reduce potential radio interference to other users, the antenna type and its gain should be so chosen that the equivalent isotropically radiated power (e.i.r.p.) is not more than that necessary for successful communication.

This radio transmitter has been approved by Industry Canada to operate with the antenna types listed in the user guide with the maximum permissible gain and required antenna impedance for each antenna type indicated. Antenna types not included in this list, having a gain greater than the maximum gain indicated for that type, are strictly prohibited for use with this device.

Cet appareil numérique de la classe A ou B est conforme à la norme NMB-003 du Canada.

Les changements ou les modifications pas expressément approuvés par la partie responsable de la conformité ont pu vider l'autorité de l'utilisateur pour actionner l'équipement.

Concernant les EVMs avec appareils radio

Le présent appareil est conforme aux CNR d'Industrie Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes : (1) l'appareil ne doit pas produire de brouillage, et (2) l'utilisateur de l'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.

Concernant les EVMs avec antennes détachables

Conformément à la réglementation d'Industrie Canada, le présent émetteur radio peut fonctionner avec une antenne d'un type et d'un gain maximal (ou inférieur) approuvé pour l'émetteur par Industrie Canada. Dans le but de réduire les risques de brouillage radioélectrique à l'intention des autres utilisateurs, il faut choisir le type d'antenne et son gain de sorte que la puissance isotrope rayonnée équivalente (p.i.r.e.) ne dépasse pas l'intensité nécessaire à l'établissement d'une communication satisfaisante.

Le présent émetteur radio a été approuvé par Industrie Canada pour fonctionner avec les types d'antenne énumérés dans le manuel d'usage et ayant un gain admissible maximal et l'impédance requise pour chaque type d'antenne. Les types d'antenne non inclus dans cette liste, ou dont le gain est supérieur au gain maximal indiqué, sont strictement interdits pour l'exploitation de l'émetteur.

【Important Notice for Users of this Product in Japan】

This development kit is NOT certified as Confirming to Technical Regulations of Radio Law of Japan

If you use this product in Japan, you are required by Radio Law of Japan to follow the instructions below with respect to this product:

1. Use this product in a shielded room or any other test facility as defined in the notification #173 issued by Ministry of Internal Affairs and Communications on March 28, 2006, based on Sub-section 1.1 of Article 6 of the Ministry's Rule for Enforcement of Radio Law of Japan,
2. Use this product only after you obtained the license of Test Radio Station as provided in Radio Law of Japan with respect to this product, or
3. Use of this product only after you obtained the Technical Regulations Conformity Certification as provided in Radio Law of Japan with respect to this product. Also, please do not transfer this product, unless you give the same notice above to the transferee. Please note that if you could not follow the instructions above, you will be subject to penalties of Radio Law of Japan.

Texas Instruments Japan Limited
(address) 24-1, Nishi-Shinjuku 6 chome, Shinjuku-ku, Tokyo, Japan

<http://www.tij.co.jp>

【ご使用にあたっての注】

本開発キットは技術基準適合証明を受けておりません。

本製品のご使用に際しては、電波法遵守のため、以下のいずれかの措置を取っていただく必要がありますのでご注意ください。

1. 電波法施行規則第6条第1項第1号に基づく平成18年3月28日総務省告示第173号で定められた電波暗室等の試験設備でご使用いただく。
2. 実験局の免許を取得後ご使用いただく。
3. 技術基準適合証明を取得後ご使用いただく。

なお、本製品は、上記の「ご使用にあたっての注意」を譲渡先、移転先に通知しない限り、譲渡、移転できないものとします。

上記を遵守頂けない場合は、電波法の罰則が適用される可能性があることをご留意ください。

日本テキサス・インスツルメンツ株式会社

東京都新宿区西新宿 6 丁目 2 4 番 1 号

西新宿三井ビル

<http://www.tij.co.jp>

EVALUATION BOARD/KIT/MODULE (EVM) WARNINGS, RESTRICTIONS AND DISCLAIMERS

For Feasibility Evaluation Only, in Laboratory/Development Environments. Unless otherwise indicated, this EVM is not a finished electrical equipment and not intended for consumer use. It is intended solely for use for preliminary feasibility evaluation in laboratory/development environments by technically qualified electronics experts who are familiar with the dangers and application risks associated with handling electrical mechanical components, systems and subsystems. It should not be used as all or part of a finished end product.

Your Sole Responsibility and Risk. You acknowledge, represent and agree that:

1. You have unique knowledge concerning Federal, State and local regulatory requirements (including but not limited to Food and Drug Administration regulations, if applicable) which relate to your products and which relate to your use (and/or that of your employees, affiliates, contractors or designees) of the EVM for evaluation, testing and other purposes.
2. You have full and exclusive responsibility to assure the safety and compliance of your products with all such laws and other applicable regulatory requirements, and also to assure the safety of any activities to be conducted by you and/or your employees, affiliates, contractors or designees, using the EVM. Further, you are responsible to assure that any interfaces (electronic and/or mechanical) between the EVM and any human body are designed with suitable isolation and means to safely limit accessible leakage currents to minimize the risk of electrical shock hazard.
3. You will employ reasonable safeguards to ensure that your use of the EVM will not result in any property damage, injury or death, even if the EVM should fail to perform as described or expected.
4. You will take care of proper disposal and recycling of the EVM's electronic components and packing materials.

Certain Instructions. It is important to operate this EVM within TI's recommended specifications and environmental considerations per the user guidelines. Exceeding the specified EVM ratings (including but not limited to input and output voltage, current, power, and environmental ranges) may cause property damage, personal injury or death. If there are questions concerning these ratings please contact a TI field representative prior to connecting interface electronics including input power and intended loads. Any loads applied outside of the specified output range may result in unintended and/or inaccurate operation and/or possible permanent damage to the EVM and/or interface electronics. Please consult the EVM User's Guide prior to connecting any load to the EVM output. If there is uncertainty as to the load specification, please contact a TI field representative. During normal operation, some circuit components may have case temperatures greater than 60°C as long as the input and output are maintained at a normal ambient operating temperature. These components include but are not limited to linear regulators, switching transistors, pass transistors, and current sense resistors which can be identified using the EVM schematic located in the EVM User's Guide. When placing measurement probes near these devices during normal operation, please be aware that these devices may be very warm to the touch. As with all electronic evaluation tools, only qualified personnel knowledgeable in electronic measurement and diagnostics normally found in development environments should use these EVMs.

Agreement to Defend, Indemnify and Hold Harmless. You agree to defend, indemnify and hold TI, its licensors and their representatives harmless from and against any and all claims, damages, losses, expenses, costs and liabilities (collectively, "Claims") arising out of or in connection with any use of the EVM that is not in accordance with the terms of the agreement. This obligation shall apply whether Claims arise under law of tort or contract or any other legal theory, and even if the EVM fails to perform as described or expected.

Safety-Critical or Life-Critical Applications. If you intend to evaluate the components for possible use in safety critical applications (such as life support) where a failure of the TI product would reasonably be expected to cause severe personal injury or death, such as devices which are classified as FDA Class III or similar classification, then you must specifically notify TI of such intent and enter into a separate Assurance and Indemnity Agreement.

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2013, Texas Instruments Incorporated

EVALUATION BOARD/KIT/MODULE (EVM) ADDITIONAL TERMS

Texas Instruments (TI) provides the enclosed Evaluation Board/Kit/Module (EVM) under the following conditions:

The user assumes all responsibility and liability for proper and safe handling of the goods. Further, the user indemnifies TI from all claims arising from the handling or use of the goods.

Should this evaluation board/kit not meet the specifications indicated in the User's Guide, the board/kit may be returned within 30 days from the date of delivery for a full refund. THE FOREGOING LIMITED WARRANTY IS THE EXCLUSIVE WARRANTY MADE BY SELLER TO BUYER AND IS IN LIEU OF ALL OTHER WARRANTIES, EXPRESSED, IMPLIED, OR STATUTORY, INCLUDING ANY WARRANTY OF MERCHANTABILITY OR FITNESS FOR ANY PARTICULAR PURPOSE. EXCEPT TO THE EXTENT OF THE INDEMNITY SET FORTH ABOVE, NEITHER PARTY SHALL BE LIABLE TO THE OTHER FOR ANY INDIRECT, SPECIAL, INCIDENTAL, OR CONSEQUENTIAL DAMAGES.

Please read the User's Guide and, specifically, the Warnings and Restrictions notice in the User's Guide prior to handling the product. This notice contains important safety information about temperatures and voltages. For additional information on TI's environmental and/or safety programs, please visit www.ti.com/esh or contact TI.

No license is granted under any patent right or other intellectual property right of TI covering or relating to any machine, process, or combination in which such TI products or services might be or are used. TI currently deals with a variety of customers for products, and therefore our arrangement with the user is not exclusive. TI assumes no liability for applications assistance, customer product design, software performance, or infringement of patents or services described herein.

REGULATORY COMPLIANCE INFORMATION

As noted in the EVM User's Guide and/or EVM itself, this EVM and/or accompanying hardware may or may not be subject to the Federal Communications Commission (FCC) and Industry Canada (IC) rules.

For EVMs **not** subject to the above rules, this evaluation board/kit/module is intended for use for ENGINEERING DEVELOPMENT, DEMONSTRATION OR EVALUATION PURPOSES ONLY and is not considered by TI to be a finished end product fit for general consumer use. It generates, uses, and can radiate radio frequency energy and has not been tested for compliance with the limits of computing devices pursuant to part 15 of FCC or ICES-003 rules, which are designed to provide reasonable protection against radio frequency interference. Operation of the equipment may cause interference with radio communications, in which case the user at his own expense will be required to take whatever measures may be required to correct this interference.

General Statement for EVMs including a radio

User Power/Frequency Use Obligations: This radio is intended for development/professional use only in legally allocated frequency and power limits. Any use of radio frequencies and/or power availability of this EVM and its development application(s) must comply with local laws governing radio spectrum allocation and power limits for this evaluation module. It is the user's sole responsibility to only operate this radio in legally acceptable frequency space and within legally mandated power limitations. Any exceptions to this are strictly prohibited and unauthorized by Texas Instruments unless user has obtained appropriate experimental/development licenses from local regulatory authorities, which is responsibility of user including its acceptable authorization.

For EVMs annotated as FCC – FEDERAL COMMUNICATIONS COMMISSION Part 15 Compliant

Caution

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

FCC Interference Statement for Class A EVM devices

This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his own expense.

FCC Interference Statement for Class B EVM devices

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

For EVMs annotated as IC – INDUSTRY CANADA Compliant

This Class A or B digital apparatus complies with Canadian ICES-003.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

Concerning EVMs including radio transmitters

This device complies with Industry Canada licence-exempt RSS standard(s). Operation is subject to the following two conditions: (1) this device may not cause interference, and (2) this device must accept any interference, including interference that may cause undesired operation of the device.

Concerning EVMs including detachable antennas

Under Industry Canada regulations, this radio transmitter may only operate using an antenna of a type and maximum (or lesser) gain approved for the transmitter by Industry Canada. To reduce potential radio interference to other users, the antenna type and its gain should be so chosen that the equivalent isotropically radiated power (e.i.r.p.) is not more than that necessary for successful communication.

This radio transmitter has been approved by Industry Canada to operate with the antenna types listed in the user guide with the maximum permissible gain and required antenna impedance for each antenna type indicated. Antenna types not included in this list, having a gain greater than the maximum gain indicated for that type, are strictly prohibited for use with this device.

Cet appareil numérique de la classe A ou B est conforme à la norme NMB-003 du Canada.

Les changements ou les modifications pas expressément approuvés par la partie responsable de la conformité ont pu vider l'autorité de l'utilisateur pour actionner l'équipement.

Concernant les EVMs avec appareils radio

Le présent appareil est conforme aux CNR d'Industrie Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes : (1) l'appareil ne doit pas produire de brouillage, et (2) l'utilisateur de l'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.

Concernant les EVMs avec antennes détachables

Conformément à la réglementation d'Industrie Canada, le présent émetteur radio peut fonctionner avec une antenne d'un type et d'un gain maximal (ou inférieur) approuvé pour l'émetteur par Industrie Canada. Dans le but de réduire les risques de brouillage radioélectrique à l'intention des autres utilisateurs, il faut choisir le type d'antenne et son gain de sorte que la puissance isotrope rayonnée équivalente (p.i.r.e.) ne dépasse pas l'intensité nécessaire à l'établissement d'une communication satisfaisante.

Le présent émetteur radio a été approuvé par Industrie Canada pour fonctionner avec les types d'antenne énumérés dans le manuel d'usage et ayant un gain admissible maximal et l'impédance requise pour chaque type d'antenne. Les types d'antenne non inclus dans cette liste, ou dont le gain est supérieur au gain maximal indiqué, sont strictement interdits pour l'exploitation de l'émetteur.

【Important Notice for Users of this Product in Japan】

This development kit is NOT certified as Confirming to Technical Regulations of Radio Law of Japan

If you use this product in Japan, you are required by Radio Law of Japan to follow the instructions below with respect to this product:

1. Use this product in a shielded room or any other test facility as defined in the notification #173 issued by Ministry of Internal Affairs and Communications on March 28, 2006, based on Sub-section 1.1 of Article 6 of the Ministry's Rule for Enforcement of Radio Law of Japan,
2. Use this product only after you obtained the license of Test Radio Station as provided in Radio Law of Japan with respect to this product, or
3. Use of this product only after you obtained the Technical Regulations Conformity Certification as provided in Radio Law of Japan with respect to this product. Also, please do not transfer this product, unless you give the same notice above to the transferee. Please note that if you could not follow the instructions above, you will be subject to penalties of Radio Law of Japan.

Texas Instruments Japan Limited
(address) 24-1, Nishi-Shinjuku 6 chome, Shinjuku-ku, Tokyo, Japan

<http://www.tij.co.jp>

【ご使用にあたっての注】

本開発キットは技術基準適合証明を受けておりません。

本製品のご使用に際しては、電波法遵守のため、以下のいずれかの措置を取っていただく必要がありますのでご注意ください。

1. 電波法施行規則第6条第1項第1号に基づく平成18年3月28日総務省告示第173号で定められた電波暗室等の試験設備でご使用いただく。
2. 実験局の免許を取得後ご使用いただく。
3. 技術基準適合証明を取得後ご使用いただく。

なお、本製品は、上記の「ご使用にあたっての注意」を譲渡先、移転先に通知しない限り、譲渡、移転できないものとします。

上記を遵守頂けない場合は、電波法の罰則が適用される可能性があることをご留意ください。

日本テキサス・インスツルメンツ株式会社

東京都新宿区西新宿 6 丁目 2 4 番 1 号

西新宿三井ビル

<http://www.tij.co.jp>

EVALUATION BOARD/KIT/MODULE (EVM) WARNINGS, RESTRICTIONS AND DISCLAIMERS

For Feasibility Evaluation Only, in Laboratory/Development Environments. Unless otherwise indicated, this EVM is not a finished electrical equipment and not intended for consumer use. It is intended solely for use for preliminary feasibility evaluation in laboratory/development environments by technically qualified electronics experts who are familiar with the dangers and application risks associated with handling electrical mechanical components, systems and subsystems. It should not be used as all or part of a finished end product.

Your Sole Responsibility and Risk. You acknowledge, represent and agree that:

1. You have unique knowledge concerning Federal, State and local regulatory requirements (including but not limited to Food and Drug Administration regulations, if applicable) which relate to your products and which relate to your use (and/or that of your employees, affiliates, contractors or designees) of the EVM for evaluation, testing and other purposes.
2. You have full and exclusive responsibility to assure the safety and compliance of your products with all such laws and other applicable regulatory requirements, and also to assure the safety of any activities to be conducted by you and/or your employees, affiliates, contractors or designees, using the EVM. Further, you are responsible to assure that any interfaces (electronic and/or mechanical) between the EVM and any human body are designed with suitable isolation and means to safely limit accessible leakage currents to minimize the risk of electrical shock hazard.
3. You will employ reasonable safeguards to ensure that your use of the EVM will not result in any property damage, injury or death, even if the EVM should fail to perform as described or expected.
4. You will take care of proper disposal and recycling of the EVM's electronic components and packing materials.

Certain Instructions. It is important to operate this EVM within TI's recommended specifications and environmental considerations per the user guidelines. Exceeding the specified EVM ratings (including but not limited to input and output voltage, current, power, and environmental ranges) may cause property damage, personal injury or death. If there are questions concerning these ratings please contact a TI field representative prior to connecting interface electronics including input power and intended loads. Any loads applied outside of the specified output range may result in unintended and/or inaccurate operation and/or possible permanent damage to the EVM and/or interface electronics. Please consult the EVM User's Guide prior to connecting any load to the EVM output. If there is uncertainty as to the load specification, please contact a TI field representative. During normal operation, some circuit components may have case temperatures greater than 60°C as long as the input and output are maintained at a normal ambient operating temperature. These components include but are not limited to linear regulators, switching transistors, pass transistors, and current sense resistors which can be identified using the EVM schematic located in the EVM User's Guide. When placing measurement probes near these devices during normal operation, please be aware that these devices may be very warm to the touch. As with all electronic evaluation tools, only qualified personnel knowledgeable in electronic measurement and diagnostics normally found in development environments should use these EVMs.

Agreement to Defend, Indemnify and Hold Harmless. You agree to defend, indemnify and hold TI, its licensors and their representatives harmless from and against any and all claims, damages, losses, expenses, costs and liabilities (collectively, "Claims") arising out of or in connection with any use of the EVM that is not in accordance with the terms of the agreement. This obligation shall apply whether Claims arise under law of tort or contract or any other legal theory, and even if the EVM fails to perform as described or expected.

Safety-Critical or Life-Critical Applications. If you intend to evaluate the components for possible use in safety critical applications (such as life support) where a failure of the TI product would reasonably be expected to cause severe personal injury or death, such as devices which are classified as FDA Class III or similar classification, then you must specifically notify TI of such intent and enter into a separate Assurance and Indemnity Agreement.

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2012, Texas Instruments Incorporated

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, enhancements, improvements and other changes to its semiconductor products and services per JESD46, latest issue, and to discontinue any product or service per JESD48, latest issue. Buyers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All semiconductor products (also referred to herein as "components") are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its components to the specifications applicable at the time of sale, in accordance with the warranty in TI's terms and conditions of sale of semiconductor products. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by applicable law, testing of all parameters of each component is not necessarily performed.

TI assumes no liability for applications assistance or the design of Buyers' products. Buyers are responsible for their products and applications using TI components. To minimize the risks associated with Buyers' products and applications, Buyers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI components or services are used. Information published by TI regarding third-party products or services does not constitute a license to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of significant portions of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI components or services with statements different from or beyond the parameters stated by TI for that component or service voids all express and any implied warranties for the associated TI component or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Buyer acknowledges and agrees that it is solely responsible for compliance with all legal, regulatory and safety-related requirements concerning its products, and any use of TI components in its applications, notwithstanding any applications-related information or support that may be provided by TI. Buyer represents and agrees that it has all the necessary expertise to create and implement safeguards which anticipate dangerous consequences of failures, monitor failures and their consequences, lessen the likelihood of failures that might cause harm and take appropriate remedial actions. Buyer will fully indemnify TI and its representatives against any damages arising out of the use of any TI components in safety-critical applications.

In some cases, TI components may be promoted specifically to facilitate safety-related applications. With such components, TI's goal is to help enable customers to design and create their own end-product solutions that meet applicable functional safety standards and requirements. Nonetheless, such components are subject to these terms.

No TI components are authorized for use in FDA Class III (or similar life-critical medical equipment) unless authorized officers of the parties have executed a special agreement specifically governing such use.

Only those TI components which TI has specifically designated as military grade or "enhanced plastic" are designed and intended for use in military/aerospace applications or environments. Buyer acknowledges and agrees that any military or aerospace use of TI components which have **not** been so designated is solely at the Buyer's risk, and that Buyer is solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI has specifically designated certain components as meeting ISO/TS16949 requirements, mainly for automotive use. In any case of use of non-designated products, TI will not be responsible for any failure to meet ISO/TS16949.

Products

Audio	www.ti.com/audio
Amplifiers	amplifier.ti.com
Data Converters	dataconverter.ti.com
DLP® Products	www.dlp.com
DSP	dsp.ti.com
Clocks and Timers	www.ti.com/clocks
Interface	interface.ti.com
Logic	logic.ti.com
Power Mgmt	power.ti.com
Microcontrollers	microcontroller.ti.com
RFID	www.ti-rfid.com
OMAP Applications Processors	www.ti.com/omap
Wireless Connectivity	www.ti.com/wirelessconnectivity

Applications

Automotive and Transportation	www.ti.com/automotive
Communications and Telecom	www.ti.com/communications
Computers and Peripherals	www.ti.com/computers
Consumer Electronics	www.ti.com/consumer-apps
Energy and Lighting	www.ti.com/energy
Industrial	www.ti.com/industrial
Medical	www.ti.com/medical
Security	www.ti.com/security
Space, Avionics and Defense	www.ti.com/space-avionics-defense
Video and Imaging	www.ti.com/video

TI E2E Community

e2e.ti.com