



Tripp Lite
1111 West 35th Street
Chicago, IL 60609 USA
Telephone: +(773) 869 1234
E-mail: saleshelp@tripplite.com

Model #: PV600

PowerVerter Ultra-Compact Inverter - Portable Power for All Applications

Highlights

- 600 watt continuous output; 1200 watt peak output (instantaneous)
- Converts 12V DC (battery) power into 110-120V AC (household) power; 3 AC outlets
- Installs in minutes (includes integrated mounting feet)
- Provides a quiet alternative to generator noise and fumes
- Includes "battery saver" low voltage alarm/shutdown

Description

Harness your vehicle's battery to efficiently power appliances, small electronics and office equipment on the road. Continuously supplies up to 600 watts of 120V AC power to 3 AC outlets from any 12V battery. Ultra-compact, lightweight metal case design is among the smallest, most rugged inverters available.

Applications

- Ideal for portable electronics, office equipment, RV and mobile appliances, video game and small entertainment systems, battery chargers and more

Package Includes

- PV600 Ultra-Compact DC-to-AC Inverter
- Instruction manual

Features

- Provides 120V AC power for a variety of mobile applications
- 600 watts continuous output power and 1200 watts peak output power (instantaneous)
- 3 AC outlets
- Ultra-compact, extruded aluminum casing stands up to the toughest environments
- Cooling fan lengthens inverter service life
- Integrated mounting feet provide safe, fixed installation
- Low battery alarm/shutdown detects low voltage and shuts down inverter
- Overload alarm/shutdown detects wattage overload on inverter outlets and shuts down inverter as a protective measure
- DC input terminals assure solid connection to battery with user-supplied cables
- Lighted on/off switch shows inverter operations in cramped or dark environments

Specifications

OUTPUT	
Frequency compatibility	60 Hz
Output watts	600W (continuous)/1200W (peak)
Output nominal voltage	120V

Output voltage regulation	Maintains PWM sine wave output voltage of 115 V AC (+/- 8 V AC)
Output frequency regulation	60 Hz (+/- 3 Hz)
Overload protection	Via set of 2 40A automotive input fuses
Outlet quantity / type	3 NEMA 5-15R
INPUT	
Recommended Electrical Service	Requires 12V DC input source capable of delivering 64A for the required duration (when used at full capacity). For automotive applications, professional hardwire installation with 80A battery system fusing is recommended.
Maximum input amps / watts	Full continuous load - 64A at 12V DC, No load - 0.95A at 12V DC, Shutdown - 150 microamps
Input connection type	Set of 2 DC bolt-down wiring terminals
Input cord length details	User supplies cabling. Minimum gauges for full load operation: 8 (6 ft max), Two 10 (8 ft max), 6 (10 ft max), 4 (15 ft max).
Voltage compatibility (VDC)	12
BATTERY	
DC system voltage (VDC)	12
LEDS ALARMS & SWITCHES	
Alarms	Dual function alarm indicates overload conditions or low DC input voltage of 10.5V or less.
Switches	Lighted on/off power switch
PHYSICAL	
Shipping Dimensions (HWD/in)	4 x 6.5 x 10.25
Shipping Dimensions (HWD/cm)	10.2 x 16.5 x 26
Shipping weight (lbs)	3
Shipping weight (kg)	1.4
Unit Dimensions (HWD/in)	2.75 x 5 x 8.25
Unit Dimensions (HWD/cm)	7 x 12.7 x 21
Unit weight (lbs)	2.5
Unit weight (kg)	1.1
Cooling method	Fan
Material of construction	Aluminum / sheet metal
ENVIRONMENTAL	
Relative Humidity	0-95% non-condensing
SPECIAL FEATURES	
Appearance	Attractive, rugged, metallic gray color inverter system
WARRANTY	

Product Warranty Period (Worldwide)	1-year limited warranty
--	-------------------------

More information, including related products, owner's manuals, and additional technical specifications, can be found online at www.tripplite.com/en/products/model.cfm?txtModelID=2651.

Copyright © 2013 Tripp Lite. All rights reserved. All trademarks are the sole property of their respective owners. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Photos may differ slightly from final products.