15mmx15mm LIGHT BAR

Part Number: DE4SURKD Hyp

Hyper Red


Features

- Uniform light emitting area.
- Easily mounted on P.C. boards or industry standard sockets.
- Flush mountable.
- Excellent on/off contrast.
- Can be used with panels and legend mounts.
- Mechanically rugged.
- RoHS compliant.

Description

The Hyper Red source color devices are made with Al-GalnP on GaAs substrate Light Emitting Diode.

Package Dimensions& Internal Circuit Diagram



DATE: JAN/20/2013 DRAWN: C.H.Han

Selection Guide	Dice	Dice Lens Type			
			Min.	Тур.	
	D Hyper Red (AlGaInP) Red Diffused	Ded Diffused	500	930	
DE4SURKD		Red Diffused	*120	*250	

Notes:

Luminous intensity/ luminous Flux: +/-15%.
* Luminous intensity value is traceable to the CIE127-2007 compliant national standards.

Electrical / Optical Characteristics at TA=25°C

Symbol	Parameter	Device	Тур.	Max.	Units	Test Conditions
λpeak	Peak Wavelength	Hyper Red	645		nm	I⊧=20mA
λD [1]	Dominant Wavelength	Hyper Red	630		nm	I⊧=20mA
Δλ1/2	Spectral Line Half-width	Hyper Red	28		nm	I⊧=20mA
С	Capacitance	Hyper Red	35		pF	VF=0V;f=1MHz
VF [2]	Forward Voltage	Hyper Red	1.95	2.5	V	I⊧=20mA
IR	Reverse Current	Hyper Red		10	uA	VR=5V

Notes:

1.Wavelength: +/-1nm. 2. Forward Voltage: +/-0.1V.


3. Wavelength value is traceable to the CIE127-2007 compliant national standards.


Absolute Maximum Ratings at TA=25°C


Parameter	Hyper Red	Units	
Power dissipation	75	mW	
DC Forward Current	30	mA	
Peak Forward Current [1]	185	mA	
Reverse Voltage	5	V	
Operating / Storage Temperature	-40°C To +85°C		
Lead Solder Temperature[2]	260°C For 3-5 Seconds		


Notes:

1. 1/10 Duty Cycle, 0.1ms Pulse Width.
2. 2mm below package base.










2. If cleaning is required, Kingbright recommends to wash components with water only. Do not use harsh organic solvents for cleaning, because they may damage the plastic parts .And the devices should not be washed for more than one minute.

CIRCUIT DESIGN NOTES

 Protective current-limiting resistors may be necessary to operate the Displays.
LEDs mounted in parallel should each be placed in series with its own current-limiting resistor.



DATE: JAN/20/2013 DRAWN: C.H.Han