

TPS54339EVM-056, 3-A, Regulator Evaluation Module

This user's guide contains information for the TPS54339EVM-056 evaluation module as well as for the TPS54339. Included are the performance specifications, schematic, and the bill of materials of the TPS54339EVM-056.

Contents

| | | |
|---|---|----|
| 1 | Introduction | 3 |
| 2 | Performance Specification Summary | 3 |
| 3 | Modifications | 3 |
| | 3.1 Output Voltage Setpoint | 3 |
| | 3.2 Output Filter and Closed-Loop Response | 4 |
| 4 | Test Setup and Results | 4 |
| | 4.1 Input/Output Connections | 4 |
| | 4.2 Start-Up Procedure | 5 |
| | 4.3 Efficiency | 5 |
| | 4.4 Load Regulation | 6 |
| | 4.5 Line Regulation | 7 |
| | 4.6 Load Transient Response | 7 |
| | 4.7 Output Voltage Ripple | 8 |
| | 4.8 Input Voltage Ripple | 9 |
| | 4.9 Start-Up | 9 |
| | 4.10 Shut-Down | 10 |
| 5 | Board Layout | 12 |
| | 5.1 Layout | 12 |
| 6 | Schematic, Bill of Materials, and Reference | 15 |
| | 6.1 Schematic | 15 |
| | 6.2 Bill of Materials | 16 |
| | 6.3 Reference | 16 |

List of Figures

| | | |
|----|---|----|
| 1 | TPS54339EVM-056 Efficiency | 5 |
| 2 | TPS54339EVM-056 Light-Load Efficiency..... | 6 |
| 3 | TPS54339EVM-056 Load Regulation, $V_{IN} = 5\text{ V}$ and $V_{IN} = 12\text{ V}$ | 6 |
| 4 | TPS54339EVM-056 Line Regulation..... | 7 |
| 5 | TPS54339EVM-056 Load Transient Response..... | 7 |
| 6 | TPS54339EVM-056 Output Voltage Ripple ($I_{OUT} = 3\text{ A}$) | 8 |
| 7 | TPS54339EVM-056 Output Voltage Ripple ($I_{OUT} = 0\text{ A}$) | 8 |
| 8 | TPS54339EVM-056 Input Voltage Ripple | 9 |
| 9 | TPS54339EVM-056 Start-Up Relative to V_{IN} with SS..... | 9 |
| 10 | TPS54339EVM-056 Start-Up Relative to EN with SS | 10 |
| 11 | TPS54339EVM-056 Shut-Down Relative to V_{IN} with SS | 10 |
| 12 | TPS54339EVM-056 Shut-Down Relative to EN with SS..... | 11 |
| 13 | Top Assembly..... | 12 |

D-CAP2 is a trademark of Texas Instruments.

| | | |
|----|--|----|
| 14 | Top Layer | 13 |
| 15 | Internal Layer 1 | 13 |
| 16 | Internal Layer 2 | 14 |
| 17 | Bottom Layer | 14 |
| 18 | TPS54339EVM-056 Schematic Diagram..... | 15 |

List of Tables

| | | |
|---|--|----|
| 1 | Input Voltage and Output Current Summary | 3 |
| 2 | TPS54339EVM-056 Performance Specifications Summary | 3 |
| 3 | Output Voltages | 4 |
| 4 | Connection and Test Points | 4 |
| 5 | Bill of Materials..... | 16 |

1 Introduction

The TPS54339 is a single, adaptive on-time, D-CAP2™-mode, synchronous buck converter requiring a low external component count. The D-CAP2™ control circuit is optimized for low-ESR output capacitors such as POSCAP, SP-CAP, or ceramic types and features fast transient response with no external compensation. The switching frequency is internally set at a nominal 600 kHz. The high-side and low-side switching MOSFETs are incorporated inside the TPS54339 package along with the gate-drive circuitry. The low drain-to-source on-resistance of the MOSFETs allows the TPS54339 to achieve high efficiencies and helps keep the junction temperature low at high-output currents. The TPS54339 dc/dc synchronous converter is designed to provide up to a 3-A output from an input voltage source of 4.5 V to 23 V. The output voltage range is from 0.76 V to 7 V. Rated input voltage and output current range for the evaluation module are given in [Table 1](#).

The TPS54339EVM-056 evaluation module circuit is a single, synchronous buck converter providing 1.05 V at 3 A from 4.5-V to 23-V input. This user's guide describes the TPS54339EVM-056 performance.

Table 1. Input Voltage and Output Current Summary

| EVM | Input Voltage Range | Output Current Range |
|-----------------|---|----------------------|
| TPS54339EVM-056 | $V_{IN} = 4.5 \text{ V to } 23 \text{ V}$ | 0 A to 3 A |

2 Performance Specification Summary

A summary of the TPS54339EVM-056 performance specifications is provided in [Table 2](#). Specifications are given for an input voltage of $V_{IN} = 12 \text{ V}$ and an output voltage of 1.05 V, unless otherwise noted. The ambient temperature is 25°C for all measurement, unless otherwise noted.

Table 2. TPS54339EVM-056 Performance Specifications Summary

| Specifications | Test Conditions | Min | Typ | Max | Unit |
|----------------------------------|--|-----|------------|-----|------------------|
| Input voltage range (V_{IN}) | | 4.5 | 12 | 23 | V |
| Output voltage | | | 1.05 | | V |
| Operating frequency | $V_{IN} = 12 \text{ V}, I_O = 1.5 \text{ A}$ | | 600 | | kHz |
| Output current range | | 0 | | 3 | A |
| Line regulation | $I_O = 1 \text{ A}$ | | +0.4/- 0.3 | | % |
| Load regulation | $V_{IN} = 12 \text{ V}$ | | +/- 0.05 | | % |
| Overcurrent limit | $V_{IN} = 12 \text{ V}, L_O = 2.2 \mu\text{H}$ | 3.5 | 4.1 | 5.7 | A |
| Output ripple voltage | $V_{IN} = 12 \text{ V}, I_O = 3 \text{ A}$ | | 15 | | mV _{PP} |
| Maximum efficiency | $V_{IN} = 5 \text{ V}, I_O = 0.7 \text{ A}$ | | 87.5 | | % |

3 Modifications

These evaluation modules are designed to provide access to the features of the TPS54339. Some modifications can be made to this module.

3.1 Output Voltage Setpoint

To change the output voltage of the EVMs, it is necessary to change the value of resistor R1. Changing the value of R1 can change the output voltage above 0.765 V. The value of R1 for a specific output voltage can be calculated using [Equation 1](#).

For output voltage from 0.76 V to 7 V:

$$V_O = 0.765 \times \left(1 + \frac{R1}{R2} \right) \quad (1)$$

Table 3 lists the R1 values for some common output voltages. For higher output voltages of 1.8 V or above, a feedforward capacitor (C4) may be required to improve phase margin. Pads for this component (C4) are provided on the printed-circuit board (PCB). Note that the resistor values given in Table 3 are standard values and not the exact value calculated using Equation 1.

Table 3. Output Voltages

| Output Voltage (V) | R1 (kΩ) | R2 (kΩ) | C4 (pF) ⁽¹⁾ | | | L1 (μH) | | | C8 + C9 + C10 (μF) | |
|--------------------|---------|---------|------------------------|-----|-----|---------|-----|-----|--------------------|-----|
| | | | Min | Typ | Max | Min | Typ | Max | Min | Max |
| 1 | 6.81 | 22.1 | 5 | 150 | 220 | 1.5 | 2.2 | 4.7 | 22 | 68 |
| 1.05 | 8.25 | 22.1 | 5 | 150 | 220 | 1.5 | 2.2 | 4.7 | 22 | 68 |
| 1.2 | 12.7 | 22.1 | 5 | | 100 | 1.5 | 2.2 | 4.7 | 22 | 68 |
| 1.5 | 21.5 | 22.1 | 5 | | 68 | 1.5 | 2.2 | 4.7 | 22 | 68 |
| 1.8 | 30.1 | 22.1 | 5 | | 22 | 2.2 | 3.3 | 4.7 | 22 | 68 |
| 2.5 | 49.9 | 22.1 | 5 | | 22 | 2.2 | 3.3 | 4.7 | 22 | 68 |
| 3.3 | 73.2 | 22.1 | 5 | | 22 | 2.2 | 3.3 | 4.7 | 22 | 68 |
| 5 | 124 | 22.1 | 5 | | 22 | 3.3 | | 4.7 | 22 | 68 |
| 6.5 | 165 | 22.1 | 5 | | 22 | 3.3 | | 4.7 | 22 | 68 |

⁽¹⁾ Optional

3.2 Output Filter and Closed-Loop Response

The TPS54339 relies on the output filter characteristics to ensure stability of the control loop. The recommended output filter components for common output voltages are given in Table 3. It may be possible for other output filter component values to provide acceptable closed-loop characteristics. R3 and TP4 are provided for convenience in breaking the control loop and measuring the closed-loop response.

4 Test Setup and Results

This section describes how to properly connect, set up, and use the TPS54339EVM-056. The section also includes test results typical for the evaluation modules and efficiency, output load regulation, output line regulation, load transient response, output voltage ripple, input voltage ripple, start-up, and switching frequency.

4.1 Input/Output Connections

The TPS54339EVM-056 is provided with input and output connectors and test points as shown in Table 4. A power supply capable of supplying 2 A must be connected to J1 through a pair of 20 AWG wires. The load must be connected to J2 through a pair of 20 AWG wires. The maximum load current capability is 3 A. Wire lengths must be minimized to reduce losses in the wires. Test point TP1 provides a place to monitor the V_{IN} input voltages with TP2 providing a convenient ground reference. TP8 is used to monitor the output voltage with TP9 as the ground reference.

Table 4. Connection and Test Points

| Reference Designator | Function |
|----------------------|--|
| J1 | V_{IN} (see Table 1 for V_{IN} range) |
| J2 | V_{OUT} , 1.05 V at 3-A maximum |
| JP1 | EN control. Connect EN to OFF to disable, connect EN to ON to enable |
| TP1 | V_{IN} test point at V_{IN} connector |
| TP2 | GND test point at V_{IN} connector |
| TP3 | EN test point |
| TP4 | Loop response measurement test point |
| TP5 | VREG5 test point |
| TP6 | Switch node test point |

Table 4. Connection and Test Points (continued)

| Reference Designator | Function |
|----------------------|--|
| TP7 | Analog ground test point |
| TP8 | Output voltage test point at V_{OUT} connector |
| TP9 | Ground test point at V_{OUT} connector |

4.2 Start-Up Procedure

1. Ensure that the jumper at JP1 (Enable control) is set from EN to OFF.
2. Apply appropriate V_{IN} voltage to V_{IN} and PGND terminals at J1.
3. Move the jumper at JP1 (Enable control) to cover EN and ON. The EVM enables the output voltage.

4.3 Efficiency

Figure 1 shows the efficiency for the TPS54339EVM-056 at an ambient temperature of 25°C.




Figure 1. TPS54339EVM-056 Efficiency

Figure 2 shows the efficiency at light loads for the TPS54339EVM-056 at an ambient temperature of 25°C.




Figure 2. TPS54339EVM-056 Light-Load Efficiency

4.4 Load Regulation

The load regulation for the TPS54339EVM-056 is shown in Figure 3.




Figure 3. TPS54339EVM-056 Load Regulation, $V_{IN} = 5\text{ V}$ and $V_{IN} = 12\text{ V}$

4.5 Line Regulation

The line regulation for the TPS54339EVM-056 is shown in Figure 4.




Figure 4. TPS54339EVM-056 Line Regulation

4.6 Load Transient Response

The TPS54339EVM-056 response to load transient is shown in Figure 5. The current step is from 0.75 A to 2.25 A. Total peak-to-peak voltage variation is as shown.




Figure 5. TPS54339EVM-056 Load Transient Response

4.7 Output Voltage Ripple

The TPS54339EVM-056 output voltage ripple is shown in Figure 6. The output current is the rated full load of 3 A.




Figure 6. TPS54339EVM-056 Output Voltage Ripple ($I_{OUT} = 3 \text{ A}$)

The TPS54339EVM-056 output voltage ripple is shown in Figure 7. The output current is 0 A (no load).




Figure 7. TPS54339EVM-056 Output Voltage Ripple ($I_{OUT} = 0 \text{ A}$)

4.8 Input Voltage Ripple

The TPS54339EVM-056 input voltage ripple is shown in Figure 8. The output current is the rated full load of 3 A.




Figure 8. TPS54339EVM-056 Input Voltage Ripple

4.9 Start-Up

The TPS54339EVM-056 start-up waveforms relative to V_{IN} and EN are shown in Figure 9 and Figure 10. $R_{LOAD} = 1 \Omega$.




Figure 9. TPS54339EVM-056 Start-Up Relative to V_{IN} with SS




Figure 10. TPS54339EVM-056 Start-Up Relative to EN with SS

4.10 Shut-Down

The TPS54339EVM-056 shut-down waveforms relative to V_{IN} and EN are shown in [Figure 11](#) and [Figure 12](#). $R_{LOAD} = 1 \Omega$.




Figure 11. TPS54339EVM-056 Shut-Down Relative to V_{IN} with SS




Figure 12. TPS54339EVM-056 Shut-Down Relative to EN with SS

5 Board Layout

This section provides description of the TPS54339EVM-056, board layout, and layer illustrations.

5.1 Layout

The board layout for the TPS54339EVM-056 is shown in [Figure 13](#) through [Figure 17](#). The top layer contains the main power traces for VIN, VO, and ground. Also on the top layer are connections for the pins of the TPS54339 and a large area filled with ground. Many of the signal traces also are located on the top side. The input decoupling capacitors are located as close to the IC as possible. The input and output connectors, test points, and all of the components are located on the top side. An analog ground (GND) area is provided on the top side. Analog ground (GND) and power ground (PGND) are connected at a single point on the top layer near C6. The two internal layers are completely dedicated to power ground planes. The bottom layer is primarily power ground. A copper pour area on the bottom layer is used to connect the switching node (SW) to the output inductor and the boost capacitor. Traces also connect enable control jumper, EN, VREG5, and LOOP test points, and the feedback trace from VOUT to the voltage setpoint divider network.




Figure 13. Top Assembly




Figure 14. Top Layer




Figure 15. Internal Layer 1




Figure 16. Internal Layer 2




Figure 17. Bottom Layer

6 Schematic, Bill of Materials, and Reference

6.1 Schematic

Figure 18 is the schematic for the TPS54339EVM-056.




Figure 18. TPS54339EVM-056 Schematic Diagram

6.2 Bill of Materials

Table 5. Bill of Materials

| RefDes | Qty | Value | Description | Size | Part Number | MFR |
|------------------------------------|-----|-------------|---|--------------------|----------------|----------|
| C1, C2 | 2 | 10uF | Capacitor, Ceramic, 25V, X5R, 20% | 1210 | Std | Std |
| C3 | 1 | 0.1uF | Capacitor, Ceramic, 50V, X7R, 10% | 1206 | Std | Std |
| C4, C8 | 0 | Open | Capacitor, Ceramic | 0603 | Std | Std |
| C5 | 1 | 0.47uF | Capacitor, Ceramic, 16V, X7R, 10% | 0603 | Std | Std |
| C6 | 1 | 8200pF | Capacitor, Ceramic, 25V, X7R, 10% | 0603 | Std | Std |
| C7 | 1 | 0.1uF | Capacitor, Ceramic, 50V, X7R, 10% | 0603 | Std | Std |
| C9, C10 | 2 | 22uF | Capacitor, Ceramic, 6.3V, X5R, 20% | 1206 | C3216X5R0J226M | TDK |
| C11 | 1 | Open | Capacitor, Ceramic | 1206 | Std | Std |
| D1 | 0 | Open | Diode, 0.5 A, 30 V, 2PIN | TUMD2 | RSX051VA-30 | Rohm |
| J1, J2 | 2 | ED555/2DS | Terminal Block, 2-pin, 6-A, 3.5mm | 0.27 x 0.25 inch | ED555/2DS | Sullins |
| JP1 | 1 | PEC03SAAN | Header, Male 3-pin, 100mil spacing | 0.100 inch x 3 | PEC03SAAN | Sullins |
| L1 | 1 | 2.2uH | Inductor, SMT, 5.5A, 14.6 mΩ | 0.256 x 0.280 inch | CLF7045T-2R2N | TDK |
| R1 | 1 | 8.25k | Resistor, Chip, 1/16W, 1% | 0603 | Std | Std |
| R2 | 1 | 22.1k | Resistor, Chip, 1/16W, 1% | 0603 | Std | Std |
| R3, R5 | 2 | 0 | Resistor, Chip, 1/16W, 1% | 0603 | Std | Std |
| R4 | 1 | 10.0k | Resistor, Chip, 1/16W, 1% | 0603 | Std | Std |
| R5 | 0 | Open | Resistor, Chip, 1/16W, 1% | 0603 | Std | Std |
| TP1, TP3, TP4, TP5, TP6, TP8 | 3 | 5000 | Test Point, Red, Thru Hole Color Keyed | 0.100 x 0.100 inch | 5000 | Keystone |
| TP2, TP7, TP9 | 3 | 5001 | Test Point, Black, Thru Hole Color Keyed | 0.100 x 0.100 inch | 5001 | Keystone |
| U1 | 1 | TPS54339DDA | IC, 4.5-23 V Input, 3-A Sync. Step-Down SWIFT Converter | SO8[DDA] | TPS54339DDA | TI |
| - | 1 | | Shunt, 100-mil, Black | 0.100 | 929950-00 | 3M |
| - | 1 | | PCB | | PWR056 | Any |

6.3 Reference

1. [TPS54339, 4.5-V to 23-V Input, 3-A Synchronous Step-Down SWIFT™ Converter with data sheet \(SLVSBT2\)](#)

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, enhancements, improvements and other changes to its semiconductor products and services per JESD46, latest issue, and to discontinue any product or service per JESD48, latest issue. Buyers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All semiconductor products (also referred to herein as "components") are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its components to the specifications applicable at the time of sale, in accordance with the warranty in TI's terms and conditions of sale of semiconductor products. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by applicable law, testing of all parameters of each component is not necessarily performed.

TI assumes no liability for applications assistance or the design of Buyers' products. Buyers are responsible for their products and applications using TI components. To minimize the risks associated with Buyers' products and applications, Buyers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI components or services are used. Information published by TI regarding third-party products or services does not constitute a license to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of significant portions of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI components or services with statements different from or beyond the parameters stated by TI for that component or service voids all express and any implied warranties for the associated TI component or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Buyer acknowledges and agrees that it is solely responsible for compliance with all legal, regulatory and safety-related requirements concerning its products, and any use of TI components in its applications, notwithstanding any applications-related information or support that may be provided by TI. Buyer represents and agrees that it has all the necessary expertise to create and implement safeguards which anticipate dangerous consequences of failures, monitor failures and their consequences, lessen the likelihood of failures that might cause harm and take appropriate remedial actions. Buyer will fully indemnify TI and its representatives against any damages arising out of the use of any TI components in safety-critical applications.

In some cases, TI components may be promoted specifically to facilitate safety-related applications. With such components, TI's goal is to help enable customers to design and create their own end-product solutions that meet applicable functional safety standards and requirements. Nonetheless, such components are subject to these terms.

No TI components are authorized for use in FDA Class III (or similar life-critical medical equipment) unless authorized officers of the parties have executed a special agreement specifically governing such use.

Only those TI components which TI has specifically designated as military grade or "enhanced plastic" are designed and intended for use in military/aerospace applications or environments. Buyer acknowledges and agrees that any military or aerospace use of TI components which have **not** been so designated is solely at the Buyer's risk, and that Buyer is solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI has specifically designated certain components as meeting ISO/TS16949 requirements, mainly for automotive use. In any case of use of non-designated products, TI will not be responsible for any failure to meet ISO/TS16949.

Products

| | |
|------------------------------|--|
| Audio | www.ti.com/audio |
| Amplifiers | amplifier.ti.com |
| Data Converters | dataconverter.ti.com |
| DLP® Products | www.dlp.com |
| DSP | dsp.ti.com |
| Clocks and Timers | www.ti.com/clocks |
| Interface | interface.ti.com |
| Logic | logic.ti.com |
| Power Mgmt | power.ti.com |
| Microcontrollers | microcontroller.ti.com |
| RFID | www.ti-rfid.com |
| OMAP Applications Processors | www.ti.com/omap |
| Wireless Connectivity | www.ti.com/wirelessconnectivity |

Applications

| | |
|-------------------------------|--|
| Automotive and Transportation | www.ti.com/automotive |
| Communications and Telecom | www.ti.com/communications |
| Computers and Peripherals | www.ti.com/computers |
| Consumer Electronics | www.ti.com/consumer-apps |
| Energy and Lighting | www.ti.com/energy |
| Industrial | www.ti.com/industrial |
| Medical | www.ti.com/medical |
| Security | www.ti.com/security |
| Space, Avionics and Defense | www.ti.com/space-avionics-defense |
| Video and Imaging | www.ti.com/video |

TI E2E Community

e2e.ti.com