

# Evaluation Board User's Guide

## ADC121S625 12-Bit, 50 kSPS to 200 kSPS, Differential Input, Micro-Power Sampling A/D Converter



## Table of Contents

1.0 Introduction	3
2.0 Board Assembly	3
3.0 Quick Start	4
3.1 Stand Alone Mode	4
3.2 Computer Mode	4
4.0 Functional Description	5
4.1 The Signal Input	5
4.2 ADC Reference Circuitry	5
4.3 ADC Clock Circuit	5
4.4 Digital Data Output	5
4.5 Power Supply Connections	5
5.0 Software Operation and Settings	6
6.0 Hardware Schematic	7
7.0 Evaluation Board Specifications	8
8.0 ADC121S625B Evaluation Board Bill of Materials	8
9.0 Tables of Test Points, Jumpers and Connectors	9

## 1.0 Introduction

The ADC121S625EVAL/RoHS Design Kit (consisting of the ADC121S625B Evaluation Board and this User's Guide) is designed to ease evaluation and design-in of the National Semiconductor ADC121S625 12-bit Analog-to-Digital Converter, which can operate at speeds up to 200 kSPS.

The evaluation board can be used in either of two modes. In the Stand-Alone or Manual mode, suitable test equipment, such as a logic analyzer, can be used with the board to evaluate the ADC121S625's performance.

In the Computer or Automatic mode, data capture and evaluation is simplified by connecting this board to National Semiconductor's Data Capture Board (order number WAVEVSN BRD 4.0) with a ribbon cable (order number WV4ADCFKABLE), which is connected to a personal computer through a USB port and running WaveVision4 software. The WaveVision4 program can be downloaded from the web at <http://www.national.com/adc>.

The WaveVision4 software operates under Microsoft Windows. The signal at the Analog Input is digitized, captured, and displayed on a PC monitor in the time and frequency domain.


The software will perform an FFT on the captured data upon command. This FFT plot shows dynamic performance in the form of SNR, SINAD, THD, SFDR and ENOB. A histogram of the captured data is also available.

The differential signal at analog inputs J2 or J3 is digitized by U1, the ADC121S625.

The ADC121S625 uses an external oscillator that is provided on this board by Y2 or J6.

## 2.0 Board Assembly

The ADC121S625B evaluation board comes fully assembled and ready for use. Refer to the Bill of Materials for a description of components, to *Figure 1* for major component placement and to *Figure 2* for the Evaluation Board schematic.



## Figure 1 Component and Test Point Locations

### 3.0 Quick Start

The ADC121S625B evaluation board may be used in the Stand-Alone mode to capture data with a logic analyzer or third party equipment, or it may be used in the Computer Mode with a WaveVision4 Data Capture (WV4) Board. In both cases, the data may be analyzed with the WaveVision4 software.

### 3.1 Stand Alone Mode

Refer to *Figure 1* for locations of test points and major components.

1. Install an appropriate crystal oscillator into socket Y2 and short pins 1 & 2 of JP5 (See *Table 1*). Alternatively, connect a signal generator with TTL logic levels to BNC connector J6 and short pins 2 & 3 of JP5. In either case, short pins 4 & 10 of J4 to provide the clock signal to the ADC121S625. If using an external source, remove the oscillator from Y2. If using an oscillator at Y2, remove the signal source from J6. The presence of a second clock source could add noise to the conversion process.
2. Connect a clean analog (non-switching) +5V power source to Power Connector J5.
3. Short pins 1 & 2 of JP3 and turn on the power supply.
4. Dynamic differential signal sources centered around ground should be connected across pins 1 & 3 of J2. Pin 2 of J2 is ground. If the source has a 50 $\Omega$  output impedance, install a 51 ohm resistor at R4. Otherwise, the signal level will be twice as large as expected. To accurately evaluate the performance of the ADC121S625, the source must be better than 90dB THD.
5. Short pins 1 & 2 and pins 3 & 4 of JP2 to provide the bias voltage of VREF for the input to the ADC when driving the ADC from J2.
6. Differential DC sources or dynamic differential signal sources centered at a DC bias point should be connected across pins 1 & 3 of J3. Pin 2 of J3 is ground.
7. Remove the shorts across pins 1 & 2 and pins 3 & 4 of JP2 when driving the ADC input from J3.
8. Select the 2.5V shunt voltage reference as VREF by shorting pins 2 & 3 of JP1 or select VA as VREF by shorting pins 1 & 2 of JP1. If it is desirable to provide an external reference

voltage, the jumper must be removed from JP1 and pin 2 may be driven directly.

9. The digital inputs and outputs are available for probing at J4.

### 3.2 Computer Mode

Refer to *Figure 1* for locations of test points and major components.

1. Run the WaveVision4 program. Version 4.2 or higher is required to interface the WV4 board with the ADC121S625B evaluation board. While the program is loading, continue below.
2. Install an appropriate crystal oscillator into socket Y2 and short pins 1 & 2 of JP5 (See *Table 1*). Alternatively, connect a signal generator with TTL logic levels to BNC connector J6 and short pins 2 & 3 of JP5.
3. Connect a USB cable between the WaveVision4 Data Capture Board and the PC running the WaveVision4 program.
4. Connect a ribbon cable (order number WV4ADCIFCABLE) between J4 of the ADC121S625B evaluation board and J3 of the WV4 board.
5. Connect a clean analog (non-switching) +5V power source to Power Connector J5.
6. Short pins 1 & 2 of JP3 and turn on the power supply. See *Section 4.5 for detailed Power Supply Information*
7. Connect a separate analog +5V power source to power connector J1 on the WV4 board and turn on the power.
8. Connect a jumper cable between TP10 (+3.3V) of the WV4 board and TP5 (3P3V) of the ADC121S625B board.
9. Perform steps 4 & 5 or 6 & 7 of section 3.1 to drive the analog inputs.
10. Perform step 8 of section 3.1 to select the reference voltage.
11. Refer to section 5.0 on Software Operation and Settings.

## 4.0 Functional Description

Table 1 describes the function of the various jumpers on the ADC121S625B evaluation board. The Evaluation Board schematic is shown in Figure 2.

Jumper	Pins 1 & 2	Pins 2 & 3
JP1	Select VA as the VREF	Select 2.5V reg. as the VREF
JP2	Short pins 1 & 2 and pins 3 & 4 to bias input pins at VREF	
JP3	Select 5P0V_REMOTE from J5	Select 5P0V from J1 (WV4S)
JP4	Enable OSC (not required)	
JP5	Select on-board clock OSC Y2	Select clock OSC at BNC J6

Table 1 Jumper Functions

### 4.1 The Signal Input

The input signal to be digitized should be applied across pins 1 & 3 of J2 or J3.

For input signals centered around ground, J2 should be utilized. Pin 2 of J2 is ground. Resistor R4 is a terminating resistor for the input source. Since all sources do not have the same output impedance, R4 is not stuffed. However, it is recommended that it is stuffed by the end user with the appropriate value that matches the source.

The DC biasing for inputs applied to J2 is supplied through JP2. Short pins 1 & 2 and 3 & 4 of JP2 to properly bias the input to VREF.

If it is desired to digitize a differential DC voltage or a dynamic signal that is already properly biased for the ADC121S625, apply the signal to be digitized across pins 1 & 3 of J3. Pin 2 of J3 is ground. When applying the input at J3, all shorts on JP2 need to be removed.

Dynamic input signals should be applied through a bandpass filter to eliminate the noise and harmonics commonly associated with signal sources. To accurately evaluate the performance of the ADC121S625, the source must be better than 90dB THD

### 4.2 ADC Reference Circuitry

This evaluation board includes the option of selecting a fixed 2.5V shunt voltage reference or VA as the reference voltage. Select the 2.5V

reference as VREF by shorting pins 2 & 3 of JP1 or select VA as VREF by shorting pins 1 & 2 of JP1. If it is desirable to provide an external reference voltage, the jumper must be removed from JP1 and pin 2 may be driven directly.

If it is desirable to change the LM4040DIM3-2.5 to an LM4040 with a different voltage, carefully remove it and adjust the value of R3 to limit the current through the LM4040.

### 4.3 ADC Clock Circuit

The crystal-based oscillator provided on the evaluation board is selected by shorting pins 1 & 2 of JP5. It is best to remove any external signal generator from J6 when using this oscillator to reduce any unnecessary noise.

This board will also accept a clock signal from an external source by connecting that source to BNC J6 and shorting pins 2 & 3 of JP5. The input applied at J6 is 50 ohm terminated by R14. The external clock signal must meet TTL input requirements. It is best to remove the oscillator at Y2 when using an external clock source to reduce any unnecessary noise.

Regardless of the clock source selected by JP5, the clock signal is designed to be routed off the ADC121S625B evaluation board to National's WV4 board. This assumes a "computer mode" operation of the evaluation board. For applications utilizing the evaluation board in manual mode, short pins 4 & 10 of J4 with a short jumper wire to provide the clock signal to the ADC121S625.

### 4.4 Digital Data Output

The serial data output from this board may be monitored at J1 or J4.

### 4.5 Power Supply Connections

When operating in "computer mode" with the WV4 Board, voltage 5P0V for VA and 3P3V for U3 must be supplied to the ADC121S625B evaluation board. For best performance from the ADC121S625, the 5P0V voltage for VA should be supplied by a separate power supply to J5. The 3P3V voltage may be pulled off the WV4 Board with a jumper wire at TP10 (WV4) and applied to TP5.

When operating in "manual mode", only voltage 5P0V needs to be applied to J5.

The 5P0V voltage needs to be set between +4.5V and +5.5V and a shorting jumper must be placed across pins 1 & 2 of JP3.

## 5.0 Software Operation and Settings

The WaveVision4 software is included with the WV4 board and the latest version can be downloaded for free from National's web site at <http://www.national.com/adc>. To install this software, follow the procedure in the WaveVision4 Board User's Guide. Once the software is installed, run it and set it up as follows:

1. Connect the WV4 board to the host computer with a USB cable.
2. From the WaveVision main menu, go to Settings, then Board Settings and do the following:  
Select the following from the WaveVision4 main menu:
  - WaveVision 4.0 (USB)
  - # of Samples: 2K to 32K, as desired
3. Apply power as specified in Section 4.5, click on the "**Test**" button and await the firmware to download.
4. Click on the "**Accept**" button.
5. After the steps outlined in Section 3.2 are completed, click on 'Acquire' then 'Samples' from the Main Menu (you can also press the *F1* shortcut key). If a dialog box opens, select 'Discard' or press the *Escape* key to start collecting new updated samples.

A plot of the selected number of samples will be displayed. Make sure there is no clipping of data samples. The samples may be further analyzed by clicking on the magnifying glass icon, then clicking and dragging across a specific area of the plot for better data inspection. See the WaveVision4 Board User's Guide for details.

To view an FFT of the data captured, click on the 'FFT' tab. This plot may be zoomed in on like the data plot. A display of dynamic performance parameters in the form of SINAD, SNR, THD, SFDR and ENOB will be displayed at the top right hand corner of the FFT plot.

Acquired data may be saved to a file. Plots may also be exported as graphics. See the Data Capture Board User's Guide for details.

## 6.0 Hardware Schematic




Figure 2 ADC121S625B Evaluation Board Schematic

## 7.0 Evaluation Board Specifications

Board Size:	3.0" x 3.0" (7.6 cm x 7.6 cm)	
Power Requirements	Min: +4.5V, 100mA	Max: +5.5V, 100 mA
Clock Frequency Range:	800 kHz to 4.0 MHz	
Analog Input	0V to 2VREF	

## 8.0 ADC121S625B Evaluation Board Bill of Materials

Item	Qty	Reference	PCB Footprint	Source	Source Part #	Value
1	7	C1,C4,C5,C6,C10,C11,C14	sm/c_1206	Digikey	445-1423-2-ND	1.0uF
2	4	C2,C3,C12,C13	sm/c_0805	Digikey	PCC1840TR-ND	0.1uF
3	2	C8,C7	sm/c_0805	Digikey	399-1142-1-ND	470pF
4	2	C15,C9	sm/c_0805			NS
5	2	D2,D1	sm/led_21	Digikey	516-1440-1-ND	RED LED
6	1	D3	DAX2/DO41	Digikey	1N4003-TPMSTR-ND	IN4003
7	1	JP1	header	Digikey	S1011E-36-ND	VREF SELECT
8	1	JP2	header	Digikey	S2041E-30-ND	HEADER 2X2
9	1	JP3	header	Digikey	S1011E-36-ND	VA SELECTION
10	1	JP4	header	Digikey	S1011E-36-ND	OSC ENABLE
11	1	JP5	header	Digikey	S1011E-36-ND	CLK SELECT
12	1	J1	rt angle header	Digikey	S5803-21-ND	WV4S
13	1	J2	header	Digikey	S1011E-36-ND	VIN_AC
14	1	J3	header	Digikey	S1011E-36-ND	VIN_DC
15	1	J4	header	Digikey	S2041E-30-ND	WV4
16	1	J5	term_block	Digikey	ED1609-ND	5P0V_REMOTE
17	1	J6	BNC	Digikey	ARF1177-ND	CLK
18	2	L1,L2	sm/l_1210	Digikey	445-15435-1-ND	100uH
19	1	R1	sm/r_0805		P2.0KATR-ND	2K
20	2	R3,R2	sm/r_0805		311-5.10KCRTR-ND	5.1K
21	6	R4,R5,R9,R10,R15,R16	sm/r_0805			NS
22	1	R6	sm/r_0805		RHM0.0ATR-ND	0
23	1	R7	sm/r_0805		RHM510CTR-ND	510
24	1	R8	sm/r_0805		P200CTR-ND	200
25	2	R14,R11	sm/r_0805		P51ACT-ND	51
26	5	TP1,TP2,TP3,TP6,TP7	header	Digikey	S1011E-36-ND	AGND
27	1	TP4	header	Digikey	S1011E-36-ND	VA
28	1	TP5	header	Digikey	S1011E-36-ND	3P3V
29	1	U1	MSOP8	National	ADC121S625CIMT	ADC121S625
30	1	U2	sm/SOT23	Digikey	LM4040DIM3-2.5TR	2.5V REF
31	1	U3	EEPROM	Digikey	AT24C02BN-10SU-1.8-ND	24C02
32	1	Y2B	OSC	Allied	EC1145-4.000M	4.0MHz OSC
33	1	Y2B	OSC_socket	Digikey	A462-ND	SOCKET
34	1	PCB	Eval Board rev 1	Adv Cir	121S725_r1	ADC121S725
35	5	2-pin jumpers	Jumper	Digikey	S9001-ND	SHUNT
36	4	Rubber Feet		Digikey	SJ5003-0-ND	BUMP



## 9.0 Test Points, Connectors, and Jumpers

### Test Points on the ADC121S625B Evaluation Board

TP1: AGND	Ground. Located at the bottom right area of the board.
TP2: AGND	Ground. Located at the center of the board.
TP3: AGND	Ground. Located at the top left area of the board.
TP4: VA	VA test point. Located at the center of the board.
TP5: 3P3V	3.3V test point. Located at the middle right area of the board.
TP6: AGND	Ground. Located at the top right corner of the board.
TP7: AGND	Ground. Located in the middle right area of the board.

### Connectors on the ADC121S625B Evaluation Board

J1: WV4S	14 pin dual row right angle male header: Connects to WV4S board.
J2: VIN_AC	Three pin male header: Differential AC input.
J3: VIN_DC	Three pin male header: Differential DC input.
J4: WV4	14 pin dual row male header: Connects to WV4 board.
J5: 5P0V_REMOTE	Terminal Block: Power connector for 5P0V.
J6: CLK_IN	BNC Connector: External clock input.

### Selection Jumpers on the ADC121S625B Evaluation Board (Refer to Table 1 in Section 4.0 for configuration details)

JP1: VREF SELECT	Selects reference source for VREF.
JP2: VBIAS	Provides DC bias for analog inputs.
JP3: VA Selection	Selects source of voltage for VA.
JP4: OSC ENABLE	Not required for OSC provided with evaluation board.
JP5: CLK_SELECT	Selects clock source (on-board oscillator or external source).

**BY USING THIS PRODUCT, YOU ARE AGREEING TO BE BOUND BY THE TERMS AND CONDITIONS OF NATIONAL SEMICONDUCTOR'S END USER LICENSE AGREEMENT. DO NOT USE THIS PRODUCT UNTIL YOU HAVE READ AND AGREED TO THE TERMS AND CONDITIONS OF THAT AGREEMENT. IF YOU DO NOT AGREE WITH THEM, CONTACT THE VENDOR WITHIN TEN (10) DAYS OF RECEIPT FOR INSTRUCTIONS ON RETURN OF THE UNUSED PRODUCT FOR A REFUND OF THE PURCHASE PRICE PAID, IF ANY.**

The ADC121S625B Evaluation Board is intended for product evaluation purposes only and is not intended for resale to end consumers, is not authorized for such use and is not designed for compliance with European EMC Directive 89/336/EEC, or for compliance with any other electromagnetic compatibility requirements.

National Semiconductor Corporation does not assume any responsibility for use of any circuitry or software supplied or described. No circuit patent licenses are implied.

#### **LIFE SUPPORT POLICY**

NATIONAL'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF THE PRESIDENT OF NATIONAL SEMICONDUCTOR CORPORATION. As used herein:

1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and whose failure to perform, when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury to the user.
2. A critical component is any component in a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.

<b>National Semiconductor Corporation Americas</b> Tel: 1-800-272-9959 Fax: 1-800-737-7018 Email: support@nsc.com	<b>National Semiconductor Europe</b> Fax: +49 (0) 1 80-530 85 86 Email: europe.support@nsc.com Deutsch Tel: +49 (0) 699508 6208 English Tel: +49 (0) 870 24 0 2171 French Tel: +49 (0) 141 91 8790	<b>National Semiconductor Asia Pacific Customer Response Group</b> Tel: 65-2544466 Fax: 65-2504466 Email: sea.support@nsc.com	<b>National Semiconductor Japan Ltd.</b> Tel: 81-3-5639-7560 Fax: 81-3-5639-7507
www.national.com			

National does not assume any responsibility for any circuitry described, no circuit patent licenses are implied and National reserves the right at any time without notice to change said circuitry and specifications.

## EVALUATION BOARD/KIT/MODULE (EVM) ADDITIONAL TERMS

Texas Instruments (TI) provides the enclosed Evaluation Board/Kit/Module (EVM) under the following conditions:

The user assumes all responsibility and liability for proper and safe handling of the goods. Further, the user indemnifies TI from all claims arising from the handling or use of the goods.

Should this evaluation board/kit not meet the specifications indicated in the User's Guide, the board/kit may be returned within 30 days from the date of delivery for a full refund. THE FOREGOING LIMITED WARRANTY IS THE EXCLUSIVE WARRANTY MADE BY SELLER TO BUYER AND IS IN LIEU OF ALL OTHER WARRANTIES, EXPRESSED, IMPLIED, OR STATUTORY, INCLUDING ANY WARRANTY OF MERCHANTABILITY OR FITNESS FOR ANY PARTICULAR PURPOSE. EXCEPT TO THE EXTENT OF THE INDEMNITY SET FORTH ABOVE, NEITHER PARTY SHALL BE LIABLE TO THE OTHER FOR ANY INDIRECT, SPECIAL, INCIDENTAL, OR CONSEQUENTIAL DAMAGES.

Please read the User's Guide and, specifically, the Warnings and Restrictions notice in the User's Guide prior to handling the product. This notice contains important safety information about temperatures and voltages. For additional information on TI's environmental and/or safety programs, please visit [www.ti.com/esh](http://www.ti.com/esh) or contact TI.

No license is granted under any patent right or other intellectual property right of TI covering or relating to any machine, process, or combination in which such TI products or services might be or are used. TI currently deals with a variety of customers for products, and therefore our arrangement with the user is not exclusive. TI assumes no liability for applications assistance, customer product design, software performance, or infringement of patents or services described herein.

## REGULATORY COMPLIANCE INFORMATION

As noted in the EVM User's Guide and/or EVM itself, this EVM and/or accompanying hardware may or may not be subject to the Federal Communications Commission (FCC) and Industry Canada (IC) rules.

For EVMs **not** subject to the above rules, this evaluation board/kit/module is intended for use for ENGINEERING DEVELOPMENT, DEMONSTRATION OR EVALUATION PURPOSES ONLY and is not considered by TI to be a finished end product fit for general consumer use. It generates, uses, and can radiate radio frequency energy and has not been tested for compliance with the limits of computing devices pursuant to part 15 of FCC or ICES-003 rules, which are designed to provide reasonable protection against radio frequency interference. Operation of the equipment may cause interference with radio communications, in which case the user at his own expense will be required to take whatever measures may be required to correct this interference.

### General Statement for EVMs including a radio

*User Power/Frequency Use Obligations:* This radio is intended for development/professional use only in legally allocated frequency and power limits. Any use of radio frequencies and/or power availability of this EVM and its development application(s) must comply with local laws governing radio spectrum allocation and power limits for this evaluation module. It is the user's sole responsibility to only operate this radio in legally acceptable frequency space and within legally mandated power limitations. Any exceptions to this are strictly prohibited and unauthorized by Texas Instruments unless user has obtained appropriate experimental/development licenses from local regulatory authorities, which is responsibility of user including its acceptable authorization.

### For EVMs annotated as FCC – FEDERAL COMMUNICATIONS COMMISSION Part 15 Compliant

#### Caution

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

### FCC Interference Statement for Class A EVM devices

This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his own expense.

### **FCC Interference Statement for Class B EVM devices**

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

### **For EVMs annotated as IC – INDUSTRY CANADA Compliant**

This Class A or B digital apparatus complies with Canadian ICES-003.

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

### **Concerning EVMs including radio transmitters**

This device complies with Industry Canada licence-exempt RSS standard(s). Operation is subject to the following two conditions: (1) this device may not cause interference, and (2) this device must accept any interference, including interference that may cause undesired operation of the device.

### **Concerning EVMs including detachable antennas**

Under Industry Canada regulations, this radio transmitter may only operate using an antenna of a type and maximum (or lesser) gain approved for the transmitter by Industry Canada. To reduce potential radio interference to other users, the antenna type and its gain should be so chosen that the equivalent isotropically radiated power (e.i.r.p.) is not more than that necessary for successful communication.

This radio transmitter has been approved by Industry Canada to operate with the antenna types listed in the user guide with the maximum permissible gain and required antenna impedance for each antenna type indicated. Antenna types not included in this list, having a gain greater than the maximum gain indicated for that type, are strictly prohibited for use with this device.

Cet appareil numérique de la classe A ou B est conforme à la norme NMB-003 du Canada.

Les changements ou les modifications pas expressément approuvés par la partie responsable de la conformité ont pu vider l'autorité de l'utilisateur pour actionner l'équipement.

### **Concernant les EVMs avec appareils radio**

Le présent appareil est conforme aux CNR d'Industrie Canada applicables aux appareils radio exempts de licence. L'exploitation est autorisée aux deux conditions suivantes : (1) l'appareil ne doit pas produire de brouillage, et (2) l'utilisateur de l'appareil doit accepter tout brouillage radioélectrique subi, même si le brouillage est susceptible d'en compromettre le fonctionnement.

### **Concernant les EVMs avec antennes détachables**

Conformément à la réglementation d'Industrie Canada, le présent émetteur radio peut fonctionner avec une antenne d'un type et d'un gain maximal (ou inférieur) approuvé pour l'émetteur par Industrie Canada. Dans le but de réduire les risques de brouillage radioélectrique à l'intention des autres utilisateurs, il faut choisir le type d'antenne et son gain de sorte que la puissance isotrope rayonnée équivalente (p.i.r.e.) ne dépasse pas l'intensité nécessaire à l'établissement d'une communication satisfaisante.

Le présent émetteur radio a été approuvé par Industrie Canada pour fonctionner avec les types d'antenne énumérés dans le manuel d'usage et ayant un gain admissible maximal et l'impédance requise pour chaque type d'antenne. Les types d'antenne non inclus dans cette liste, ou dont le gain est supérieur au gain maximal indiqué, sont strictement interdits pour l'exploitation de l'émetteur.

## **【Important Notice for Users of this Product in Japan】**

**This development kit is NOT certified as Confirming to Technical Regulations of Radio Law of Japan**

If you use this product in Japan, you are required by Radio Law of Japan to follow the instructions below with respect to this product:

1. Use this product in a shielded room or any other test facility as defined in the notification #173 issued by Ministry of Internal Affairs and Communications on March 28, 2006, based on Sub-section 1.1 of Article 6 of the Ministry's Rule for Enforcement of Radio Law of Japan,
2. Use this product only after you obtained the license of Test Radio Station as provided in Radio Law of Japan with respect to this product, or
3. Use of this product only after you obtained the Technical Regulations Conformity Certification as provided in Radio Law of Japan with respect to this product. Also, please do not transfer this product, unless you give the same notice above to the transferee. Please note that if you could not follow the instructions above, you will be subject to penalties of Radio Law of Japan.

**Texas Instruments Japan Limited**  
**(address) 24-1, Nishi-Shinjuku 6 chome, Shinjuku-ku, Tokyo, Japan**

<http://www.tij.co.jp>

### **【ご使用にあたっての注】**

本開発キットは技術基準適合証明を受けておりません。

本製品のご使用に際しては、電波法遵守のため、以下のいずれかの措置を取っていただく必要がありますのでご注意ください。

1. 電波法施行規則第6条第1項第1号に基づく平成18年3月28日総務省告示第173号で定められた電波暗室等の試験設備でご使用いただく。
2. 実験局の免許を取得後ご使用いただく。
3. 技術基準適合証明を取得後ご使用いただく。

なお、本製品は、上記の「ご使用にあたっての注意」を譲渡先、移転先に通知しない限り、譲渡、移転できないものとします。

上記を遵守頂けない場合は、電波法の罰則が適用される可能性があることをご留意ください。

日本テキサス・インスツルメンツ株式会社

東京都新宿区西新宿 6 丁目 2 4 番 1 号

西新宿三井ビル

<http://www.tij.co.jp>

## EVALUATION BOARD/KIT/MODULE (EVM) WARNINGS, RESTRICTIONS AND DISCLAIMERS

**For Feasibility Evaluation Only, in Laboratory/Development Environments.** Unless otherwise indicated, this EVM is not a finished electrical equipment and not intended for consumer use. It is intended solely for use for preliminary feasibility evaluation in laboratory/development environments by technically qualified electronics experts who are familiar with the dangers and application risks associated with handling electrical mechanical components, systems and subsystems. It should not be used as all or part of a finished end product.

Your Sole Responsibility and Risk. You acknowledge, represent and agree that:

1. You have unique knowledge concerning Federal, State and local regulatory requirements (including but not limited to Food and Drug Administration regulations, if applicable) which relate to your products and which relate to your use (and/or that of your employees, affiliates, contractors or designees) of the EVM for evaluation, testing and other purposes.
2. You have full and exclusive responsibility to assure the safety and compliance of your products with all such laws and other applicable regulatory requirements, and also to assure the safety of any activities to be conducted by you and/or your employees, affiliates, contractors or designees, using the EVM. Further, you are responsible to assure that any interfaces (electronic and/or mechanical) between the EVM and any human body are designed with suitable isolation and means to safely limit accessible leakage currents to minimize the risk of electrical shock hazard.
3. You will employ reasonable safeguards to ensure that your use of the EVM will not result in any property damage, injury or death, even if the EVM should fail to perform as described or expected.
4. You will take care of proper disposal and recycling of the EVM's electronic components and packing materials.

**Certain Instructions.** It is important to operate this EVM within TI's recommended specifications and environmental considerations per the user guidelines. Exceeding the specified EVM ratings (including but not limited to input and output voltage, current, power, and environmental ranges) may cause property damage, personal injury or death. If there are questions concerning these ratings please contact a TI field representative prior to connecting interface electronics including input power and intended loads. Any loads applied outside of the specified output range may result in unintended and/or inaccurate operation and/or possible permanent damage to the EVM and/or interface electronics. Please consult the EVM User's Guide prior to connecting any load to the EVM output. If there is uncertainty as to the load specification, please contact a TI field representative. During normal operation, some circuit components may have case temperatures greater than 60°C as long as the input and output are maintained at a normal ambient operating temperature. These components include but are not limited to linear regulators, switching transistors, pass transistors, and current sense resistors which can be identified using the EVM schematic located in the EVM User's Guide. When placing measurement probes near these devices during normal operation, please be aware that these devices may be very warm to the touch. As with all electronic evaluation tools, only qualified personnel knowledgeable in electronic measurement and diagnostics normally found in development environments should use these EVMs.

**Agreement to Defend, Indemnify and Hold Harmless.** You agree to defend, indemnify and hold TI, its licensors and their representatives harmless from and against any and all claims, damages, losses, expenses, costs and liabilities (collectively, "Claims") arising out of or in connection with any use of the EVM that is not in accordance with the terms of the agreement. This obligation shall apply whether Claims arise under law of tort or contract or any other legal theory, and even if the EVM fails to perform as described or expected.

**Safety-Critical or Life-Critical Applications.** If you intend to evaluate the components for possible use in safety critical applications (such as life support) where a failure of the TI product would reasonably be expected to cause severe personal injury or death, such as devices which are classified as FDA Class III or similar classification, then you must specifically notify TI of such intent and enter into a separate Assurance and Indemnity Agreement.

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265  
Copyright © 2012, Texas Instruments Incorporated

## IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, enhancements, improvements and other changes to its semiconductor products and services per JESD46, latest issue, and to discontinue any product or service per JESD48, latest issue. Buyers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All semiconductor products (also referred to herein as "components") are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its components to the specifications applicable at the time of sale, in accordance with the warranty in TI's terms and conditions of sale of semiconductor products. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by applicable law, testing of all parameters of each component is not necessarily performed.

TI assumes no liability for applications assistance or the design of Buyers' products. Buyers are responsible for their products and applications using TI components. To minimize the risks associated with Buyers' products and applications, Buyers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any patent right, copyright, mask work right, or other intellectual property right relating to any combination, machine, or process in which TI components or services are used. Information published by TI regarding third-party products or services does not constitute a license to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of significant portions of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI components or services with statements different from or beyond the parameters stated by TI for that component or service voids all express and any implied warranties for the associated TI component or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

Buyer acknowledges and agrees that it is solely responsible for compliance with all legal, regulatory and safety-related requirements concerning its products, and any use of TI components in its applications, notwithstanding any applications-related information or support that may be provided by TI. Buyer represents and agrees that it has all the necessary expertise to create and implement safeguards which anticipate dangerous consequences of failures, monitor failures and their consequences, lessen the likelihood of failures that might cause harm and take appropriate remedial actions. Buyer will fully indemnify TI and its representatives against any damages arising out of the use of any TI components in safety-critical applications.

In some cases, TI components may be promoted specifically to facilitate safety-related applications. With such components, TI's goal is to help enable customers to design and create their own end-product solutions that meet applicable functional safety standards and requirements. Nonetheless, such components are subject to these terms.

No TI components are authorized for use in FDA Class III (or similar life-critical medical equipment) unless authorized officers of the parties have executed a special agreement specifically governing such use.

Only those TI components which TI has specifically designated as military grade or "enhanced plastic" are designed and intended for use in military/aerospace applications or environments. Buyer acknowledges and agrees that any military or aerospace use of TI components which have **not** been so designated is solely at the Buyer's risk, and that Buyer is solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI has specifically designated certain components as meeting ISO/TS16949 requirements, mainly for automotive use. In any case of use of non-designated products, TI will not be responsible for any failure to meet ISO/TS16949.

### Products

Audio	<a href="http://www.ti.com/audio">www.ti.com/audio</a>
Amplifiers	<a href="http://amplifier.ti.com">amplifier.ti.com</a>
Data Converters	<a href="http://dataconverter.ti.com">dataconverter.ti.com</a>
DLP® Products	<a href="http://www.dlp.com">www.dlp.com</a>
DSP	<a href="http://dsp.ti.com">dsp.ti.com</a>
Clocks and Timers	<a href="http://www.ti.com/clocks">www.ti.com/clocks</a>
Interface	<a href="http://interface.ti.com">interface.ti.com</a>
Logic	<a href="http://logic.ti.com">logic.ti.com</a>
Power Mgmt	<a href="http://power.ti.com">power.ti.com</a>
Microcontrollers	<a href="http://microcontroller.ti.com">microcontroller.ti.com</a>
RFID	<a href="http://www.ti-rfid.com">www.ti-rfid.com</a>
OMAP Applications Processors	<a href="http://www.ti.com/omap">www.ti.com/omap</a>
Wireless Connectivity	<a href="http://www.ti.com/wirelessconnectivity">www.ti.com/wirelessconnectivity</a>

### Applications

Automotive and Transportation	<a href="http://www.ti.com/automotive">www.ti.com/automotive</a>
Communications and Telecom	<a href="http://www.ti.com/communications">www.ti.com/communications</a>
Computers and Peripherals	<a href="http://www.ti.com/computers">www.ti.com/computers</a>
Consumer Electronics	<a href="http://www.ti.com/consumer-apps">www.ti.com/consumer-apps</a>
Energy and Lighting	<a href="http://www.ti.com/energy">www.ti.com/energy</a>
Industrial	<a href="http://www.ti.com/industrial">www.ti.com/industrial</a>
Medical	<a href="http://www.ti.com/medical">www.ti.com/medical</a>
Security	<a href="http://www.ti.com/security">www.ti.com/security</a>
Space, Avionics and Defense	<a href="http://www.ti.com/space-avionics-defense">www.ti.com/space-avionics-defense</a>
Video and Imaging	<a href="http://www.ti.com/video">www.ti.com/video</a>

### TI E2E Community

[e2e.ti.com](http://e2e.ti.com)