



**Tripp Lite**  
1111 West 35th Street  
Chicago, IL 60609 USA  
Telephone: +(773) 869 1234  
E-mail: [saleshelp@tripplite.com](mailto:saleshelp@tripplite.com)

Model #: U209-004

### 4-Port USB to Serial Adapter (USB-A Male to 4x DB9M)

#### Highlights

- Connect up to 4 serial devices (RS-232) through a single USB port
- Plug-and-play design
- No external power needed



#### Description

Tripp Lite's USB to serial adapter enables up to 4 serial devices (RS-232) to be connected to a computer through a single USB port. Perfect for applications where there are insufficient or no serial ports available. Use with serial devices such as touch screen monitors, digital cameras, card readers and printers. Each channel is capable of functioning at a 460.8 Mbps data transfer rate. A CD with drivers is included (Windows 98, ME, 2000, NT, XP). Plug-and-play/hot-swappable allows you to add or remove a device at any time. Does not require any external power. Tripp Lite warrants this product to be free from defects in materials and workmanship for 5 years.

#### System Requirements

- Available USB port on the PC (it is recommended to connect adapter directly to the PC and not through a USB HUB).
- CD-ROM to load drivers from supplied CD onto PC



#### Package Includes

- USB to Serial Adapter USBA to DB9M
- Driver CD
- Serial Port Tester

#### Features

- Connect a PDA, digital camera, modem or ISDN terminal to a computer through a USB port
- Upgrades a traditional RS-232 serial port to USB
- Connectors: USB-A male/(4x) DB9 male
- Comes standard with 16550 universal asynchronous receiver/transmitters (UART's) containing 16 byte first-in- first-out (FIFO) storage devices. This in conjunction with the USB micro controller FIFO's, helps relieve the CPU of excess interrupts by buffering both the received and transmitted data
- Does not require external power
- Plug-and-play/hot-swappable allows you to add or remove a device at any time
- Supports data transfer rates over 460.8Mbps
- Supports DB25 serial devices by connecting Tripp Lite's AT serial gold adapter (# P100-000)
- Compatible with Windows 98/SE, ME, NT, 2000 and XP
- CD with drivers included

## Specifications

| OVERVIEW             |   |
|----------------------|---|
| Intended Application | Connecting Peripherals  |
| Cable Type           | USB   |
| UPC ASSIGNMENT       |   |
| Unit Carton UPC#     | 037332118905  |
| PHYSICAL             |   |
| Color                | Beige   |
| Style                | USB   |
| CONNECTIONS          |   |
| Connector A          | <br>USB A (MALE) |
| Connector B          | <br>DB9 (MALE)   |

## Related Items

### Optional Products

| Related Model              | Description  | Qty. |
|----------------------------|--|------|
| <a href="#">U022-006</a>   | 6-ft. USB2.0 A/B Gold Device Cable (A Male to B Male)            | 1    |
| <a href="#">U022-010</a>   | 10-ft. USB2.0 A/B Gold Device Cable (A Male to B Male)           | 1    |
| <a href="#">U024-006</a>   | 6-ft. USB A/A Gold Extension Cable for USB2.0 Cable (USB-A M/F)  | 1    |
| <a href="#">U024-010</a>   | 10-ft. USB A/A Gold Extension Cable for USB2.0 Cable (USB-A M/F) | 1    |
| <a href="#">U209-000-R</a> | USB to Serial Adapter (USB-A Male to DB9M)                       | 1    |
| <a href="#">U222-004-R</a> | 4-Port USB2.0 Ultra-Mini Hub                                     | 1    |

More information, including related products, owner's manuals, and additional technical specifications, can be found online at [www.tripplite.com/en/products/model.cfm?txtModelID=2575](http://www.tripplite.com/en/products/model.cfm?txtModelID=2575).

Copyright © 2013 Tripp Lite. All rights reserved. All trademarks are the sole property of their respective owners. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Photos may differ slightly from final products.